

A.C. Secondary Voltage - Selection Guide

Power

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
266M2	117/234V 50/60 Hz.	1.25V	1.25 A	24
166F2	115V 60 Hz.	2.5V	0.25 A	21
166G2	115V 60 Hz.	2.5V	0.5 A	21
166J2	115V 60 Hz.	2.5V	1.0 A	21
166K2	115V 60 Hz.	2.5V	1.5 A	21
166L2	115V 60 Hz.	2.5V	2.5 A	21
166M2	115V 60 Hz.	2.5V	3.0 A	21
266M2	117/234V 50/60 Hz.	2.5V	3.0 A	24
166Q2	115V 60 Hz.	2.5V	6.0 A	21
266M5	117/234V 50/60 Hz.	2.5V	6.0 A	24
166S2	115V 60 Hz.	2.5V	10.0 A	21
165Z3	115V 60 Hz.	3V	50.0 A	19
266F6	117/234V 50/60 Hz.	3.15V	0.6 A	24
266GB6	117/234V 50/60 Hz.	3.15V	1.2 A	24
266J6	117/234V 50/60 Hz.	3.15V	2.0 A	24
266JB6	117/234V 50/60 Hz.	3.15V	2.4 A	24
266L6	117/234V 50/60 Hz.	3.15V	4.0 A	24
266M6	117/234V 50/60 Hz.	3.15V	6.0 A	24
266PA6	117/234V 50/60 Hz.	3.15V	12.0 A	24
266S6	117/234V 50/60 Hz.	3.15V	20.0 A	24
266V6B	117/234V 50/60 Hz.	3.15V	40.0 A	24
266G9	117/234V 50/60 Hz.	4.5V	1.0 A	24
161C10	115V 60 Hz.	5V	0.1 A	12
160D10	115/230V 50/60 Hz.	5V	0.18 A	12
161D10	115V 60 Hz.	5V	0.18 A	12
162D10	115/230V 50/60 Hz.	5V	0.22 A	14
164D10	115V 50/60 Hz.	5V	0.22 A	14
160F10	115/230V 50/60 Hz.	5V	0.24 A	12
161FA10	115V 60 Hz.	5V	0.24 A	12
166F5	115V 60 Hz.	5V	0.25 A	21
162E10	115/230V 50/60 Hz.	5V	0.5 A	14
183E10	115/230V 50/60 Hz.	5V	0.5 A	16
229E10	115/230V 50/60 Hz.	5V	0.5 A	17
164E10	115V 50/60 Hz.	5V	0.5 A	14
166G5	115V 60 Hz.	5V	0.5 A	21
160G10	115/230V 50/60 Hz.	5V	0.88 A	12
161GA10	115V 60 Hz.	5V	0.88 A	12
183F10	115/230V 50/60 Hz.	5V	1.0 A	16
166J5	115V 60 Hz.	5V	1.0 A	21
162F10	115/230V 50/60 Hz.	5V	1.2 A	14
229A10	115/230V 50/60 Hz.	5V	1.2 A	17
164F10	115V 50/60 Hz.	5V	1.2 A	14
160J10	115/230V 50/60 Hz.	5V	2.0 A	12
183G10	115/230V 50/60 Hz.	5V	2.0 A	16
161J10	115V 60 Hz.	5V	2.0 A	12
166L5	115V 60 Hz.	5V	2.0 A	21
162G10	115/230V 50/60 Hz.	5V	2.4 A	14
229B10	115/230V 50/60 Hz.	5V	2.4 A	17
164G10	115V 50/60 Hz.	5V	2.4 A	14
166MS	115V 60 Hz.	5V	3.0 A	21
167M5	115V 60 Hz.	5V	3.0 A	31
266M5	117/234V 50/60 Hz.	5V	3.0 A	24
162H10	115/230V 50/60 Hz.	5V	4.0 A	14
183H10	115/230V 50/60 Hz.	5V	4.0 A	16
164H10	115V 50/60 Hz.	5V	4.0 A	14
160H10	115/230V 50/60 Hz.	5V	4.8 A	12
229C10	115/230V 50/60 Hz.	5V	4.8 A	17
161H10	115V 60 Hz.	5V	4.8 A	12
185C10	115/230V 50/60 Hz.	5V	5.0 A	33
183J10	115/230V 50/60 Hz.	5V	6.0 A	16
167Q5	115V 60 Hz.	5V	6.0 A	31
162J10	115/230V 50/60 Hz.	5V	7.2 A	14
164J10	115V 50/60 Hz.	5V	7.2 A	14
166R5	115V 60 Hz.	5V	8.0 A	21
166RS	115V 60 Hz.	5V	8.0 A	21
167R5	115V 60 Hz.	5V	8.0 A	31
185D10	115/230V 50/60 Hz.	5V	8.6 A	33
229D10	115/230V 50/60 Hz.	5V	9.6 A	17
166S5	115V 60 Hz.	5V	10.0 A	21
167S5	115V 60 Hz.	5V	10.0 A	31
183K10	115/230V 50/60 Hz.	5V	11.2 A	16
166U5	115V 60 Hz.	5V	15.0 A	21
167U5	115V 60 Hz.	5V	15.0 A	31
185E10	115/230V 50/60 Hz.	5V	16.0 A	33
166V5	115V 60 Hz.	5V	20.0 A	21
167V5	115V 60 Hz.	5V	20.0 A	31
185F10	115/230V 50/60 Hz.	5V	26.0 A	33
165X5	115V 60 Hz.	5V	30.0 A	19
167X5	115V 60 Hz.	5V	30.0 A	31
185G10	115/230V 50/60 Hz.	5V	35.0 A	33
266E12	117/234V 50/60 Hz.	6V	0.3 A	24
266F12B	117/234V 50/60 Hz.	6V	0.6 A	24
266F12C	117/234V 50/60 Hz.	6V	0.7 A	24
266GD12	117/234V 50/60 Hz.	6V	1.4 A	24
266JA12	117/234V 50/60 Hz.	6V	2.0 A	24
266JB12	117/234V 50/60 Hz.	6V	2.4 A	24
182K6	117/234V 50/60 Hz.	6V	2.5 A	35
266LA12	117/234V 50/60 Hz.	6V	4.0 A	24
182L6	117/234V 50/60 Hz.	6V	5.0 A	35
266N12B	117/234V 50/60 Hz.	6V	8.0 A	24
182N6	117/234V 50/60 Hz.	6V	8.34 A	35
266PA12	117/234V 50/60 Hz.	6V	12.0 A	24
182Q6	117/234V 50/60 Hz.	6V	13.34 A	35
161C12	115V 60 Hz.	6.3V	0.08 A	12
166C12	115V 60 Hz.	6.3V	0.1 A	21
160D12	115/230V 50/60 Hz.	6.3V	0.14 A	12
161D12	115V 60 Hz.	6.3V	0.14 A	12
166E6	115V 60 Hz.	6.3V	0.15 A	21
162D12	115/230V 50/60 Hz.	6.3V	0.18 A	14
164D12	115V 50/60 Hz.	6.3V	0.18 A	14

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
160F12	115/230V 50/60 Hz.	6.3V	0.2 A	12
161FA12	115V 60 Hz.	6.3V	0.2 A	12
166F6	115V 60 Hz.	6.3V	0.3 A	21
266F6	117/234V 50/60 Hz.	6.3V	0.3 A	24
162E12	115/230V 50/60 Hz.	6.3V	0.4 A	14
183E12	115/230V 50/60 Hz.	6.3V	0.4 A	16
229E12	115/230V 50/60 Hz.	6.3V	0.4 A	17
164E12	115V 50/60 Hz.	6.3V	0.4 A	14
166G6	115V 60 Hz.	6.3V	0.6 A	21
266GB6	117/234V 50/60 Hz.	6.3V	0.6 A	24
266F12	117/234V 50/60 Hz.	6.3V	0.6 A	24
160G12	115/230V 50/60 Hz.	6.3V	0.7 A	12
161GA12	115V 60 Hz.	6.3V	0.7 A	12
183F12	115/230V 50/60 Hz.	6.3V	0.8 A	16
229A12	115/230V 50/60 Hz.	6.3V	0.9 A	17
162F12	115/230V 50/60 Hz.	6.3V	1.0 A	14
164F12	115V 50/60 Hz.	6.3V	1.0 A	14
166J6	115V 60 Hz.	6.3V	1.0 A	21
266J6	117/234V 50/60 Hz.	6.3V	1.0 A	24
266G12	117/234V 50/60 Hz.	6.3V	1.0 A	24
166K6	115V 60 Hz.	6.3V	1.2 A	21
266JB6	117/234V 50/60 Hz.	6.3V	1.2 A	24
166K6B	117V 50/60 Hz.	6.3V	1.2 A	21
160K12	115/230V 50/60 Hz.	6.3V	1.6 A	12
183G12	115/230V 50/60 Hz.	6.3V	1.6 A	16
161K12	115V 60 Hz.	6.3V	1.6 A	12
229B12	115/230V 50/60 Hz.	6.3V	1.8 A	17
162G12	115/230V 50/60 Hz.	6.3V	2.0 A	14
164G12	115V 50/60 Hz.	6.3V	2.0 A	14
166L6	115V 60 Hz.	6.3V	2.0 A	21
266L6	117/234V 50/60 Hz.	6.3V	2.0 A	24
266J12	117/234V 50/60 Hz.	6.3V	2.0 A	24
266M6	117/234V 50/60 Hz.	6.3V	3.0 A	24
266K12	117/234V 50/60 Hz.	6.3V	3.0 A	24
166M6	117V 50/60 Hz.	6.3V	3.0 A	21
162H12	115/230V 50/60 Hz.	6.3V	3.2 A	14
183H12	115/230V 50/60 Hz.	6.3V	3.2 A	16
164H12	115V 50/60 Hz.	6.3V	3.2 A	14
229C12	115/230V 50/60 Hz.	6.3V	3.8 A	17
160H12	115/230V 50/60 Hz.	6.3V	4.0 A	12
185C12	115/230V 50/60 Hz.	6.3V	4.0 A	33
161H12	115V 60 Hz.	6.3V	4.0 A	12
166N6	115V 60 Hz.	6.3V	4.0 A	21
167N6	115V 60 Hz.	6.3V	4.0 A	31
266L12B	117/234V 50/60 Hz.	6.3V	4.0 A	24
183J12	115/230V 50/60 Hz.	6.3V	4.8 A	16
266L12	117/234V 50/60 Hz.	6.3V	5.0 A	24
162J12	115/230V 50/60 Hz.	6.3V	5.7 A	14
164J12	115V 50/60 Hz.	6.3V	5.7 A	14
166Q6	115V 60 Hz.	6.3V	6.0 A	21
167Q6	115V 60 Hz.	6.3V	6.0 A	31
266PA6	117/234V 50/60 Hz.	6.3V	6.0 A	24
266M12	117/234V 50/60 Hz.	6.3V	6.0 A	24
185D12	115/230V 50/60 Hz.	6.3V	6.8 A	33
229D12	115/230V 50/60 Hz.	6.3V	7.6 A	17
167R6	115V 60 Hz.	6.3V	8.0 A	31
266N12	117/234V 50/60 Hz.	6.3V	8.0 A	24
183K12	115/230V 50/60 Hz.	6.3V	8.8 A	16
166S6	115V 60 Hz.	6.3V	10.0 A	21
167S6	115V 60 Hz.	6.3V	10.0 A	31
266S6	117/234V 50/60 Hz.	6.3V	10.0 A	24
167T6	115V 60 Hz.	6.3V	12.0 A	31
185E12	115/230V 50/60 Hz.	6.3V	12.6 A	33
167U6	115V 60 Hz.	6.3V	16.0 A	31
266V6B	117/234V 50/60 Hz.	6.3V	20.0 A	24
185F12	115/230V 50/60 Hz.	6.3V	20.6 A	33
185G12	115/230V 50/60 Hz.	6.3V	28.0 A	33
166G7	115V 60 Hz.	7V	0.7 A	21
266G14	117/234V 50/60 Hz.	7V	1.0 A	24
266J14	117/234V 50/60 Hz.	7V	2.0 A	24
266L14	117/234V 50/60 Hz.	7V	4.0 A	24
266PA14	117/234V 50/60 Hz.	7V	12.0 A	24
166U7	115V 60 Hz.	7.5V	15.0 A	21
167U7	115V 60 Hz.	7.5V	15.0 A	31
165V7	115V 60 Hz.	7.5V	21.0 A	19
167V7	115V 60 Hz.	7.5V	21.0 A	31
161C16	115V 60 Hz.	8V	0.0625 A	12
160D16	115/230V 50/60 Hz.	8V	0.11 A	12
161D16	115V 60 Hz.	8V	0.11 A	12
162D16	115/230V 50/60 Hz.	8V	0.14 A	14
164D16	115V 50/60 Hz.	8V	0.14 A	14
160E16	115/230V 50/60 Hz.	8V	0.15 A	12
161EA16	115V 60 Hz.	8V	0.15 A	12
162E16	115/230V 50/60 Hz.	8V	0.3 A	14
183E16	115/230V 50/60 Hz.	8V	0.3 A	16
229E16	115/230V 50/60 Hz.	8V	0.3 A	17
164E16	115V 50/60 Hz.	8V	0.3 A	14
166G8	115V 60 Hz.	8V	0.5 A	21
160F16	115/230V 50/60 Hz.	8V	0.52 A	12
161FA16	115V 60 Hz.	8V	0.52 A	12
183F16	115/230V 50/60 Hz.	8V	0.62 A	16
229A16	115/230V 50/60 Hz.	8V	0.7 A	17
162F16	115/230V 50/60 Hz.	8V	0.8 A	14
164F16	115V 50/60 Hz.	8V	0.8 A	14
266G16	117/234V 50/60 Hz.	8V	1.0 A	24
183G16	115/230V 50/60 Hz.	8V	1.25 A	16
160G16	115/230V 50/60 Hz.	8V	1.28 A	12
161G16	115V 60 Hz.	8V	1.28 A	12
229B16	115/230V 50/60 Hz.	8V	1.4 A	17
162G16	115/230V 50/60 Hz.	8V	1.6 A	14

EUROPE

Basingstoke, UK 01256 812812

AUSTRALIA

Queenstown, Australia 61-8-8240-2244

www.hammondmfg.com



CANADA

Guelph, Ontario (519) 822-2960
St. Laurent, Quebec (514) 343-9010

USA

Cheektow

A.C. Secondary Voltage - Selection Guide

Power

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
164G16	115V 50/60 Hz.	8V	1.6 A	14
266J16	117/234V 50/60 Hz.	8V	2.0 A	24
162H16	115/230V 50/60 Hz.	8V	2.5 A	14
183H16	115/230V 50/60 Hz.	8V	2.5 A	16
164H16	115V 50/60 Hz.	8V	2.5 A	14
160H16	115/230V 50/60 Hz.	8V	3.0 A	12
229C16	115/230V 50/60 Hz.	8V	3.0 A	17
161H16	115V 60 Hz.	8V	3.0 A	12
185C16	115/230V 50/60 Hz.	8V	3.2 A	33
183J16	115/230V 50/60 Hz.	8V	3.8 A	16
266L16	117/234V 50/60 Hz.	8V	4.4 A	24
162J16	115/230V 50/60 Hz.	8V	4.5 A	14
164J16	115V 50/60 Hz.	8V	4.5 A	14
185D16	115/230V 50/60 Hz.	8V	5.4 A	33
229D16	115/230V 50/60 Hz.	8V	6.0 A	17
266M16	117/234V 50/60 Hz.	8V	6.0 A	24
183K16	115/230V 50/60 Hz.	8V	7.0 A	16
185E16	115/230V 50/60 Hz.	8V	10.0 A	33
185F16	115/230V 50/60 Hz.	8V	16.2 A	33
185G16	115/230V 50/60 Hz.	8V	22.0 A	33
166J8	115V 60 Hz.	8.5V C.T.	1.0 A	21
166L8	115V 60 Hz.	8.5V C.T.	2.0 A	21
166M8	115V 60 Hz.	8.5V C.T.	3.0 A	21
166N8	115V 60 Hz.	8.5V C.T.	4.0 A	21
166B18	115V 60 Hz.	9V	0.06 A	21
166G9	115V 60 Hz.	9V C.T.	0.5 A	21
266G9	117/234V 50/60 Hz.	9V C.T.	0.5 A	24
182H9	117/234V 50/60 Hz.	9V	1.66 A	35
266K18	117/234V 50/60 Hz.	9V	3.0 A	24
182K9	117/234V 50/60 Hz.	9V	3.34 A	35
182M9	117/234V 50/60 Hz.	9V	5.56 A	35
266M18	117/234V 50/60 Hz.	9V	6.0 A	24
182N9	117/234V 50/60 Hz.	9V	8.88 A	35
266P18	117/234V 50/60 Hz.	9V	10.0 A	24
182Q9	117/234V 50/60 Hz.	9V	13.34 A	35
161C10	115V 60 Hz.	10V C.T.	0.05 A	12
160D10	115/230V 50/60 Hz.	10V C.T.	0.09 A	12
160D20	115/230V 50/60 Hz.	10V	0.09 A	12
161D10	115V 60 Hz.	10V C.T.	0.09 A	12
161D20	115V 60 Hz.	10V	0.09 A	12
226D	115V 60 Hz.	10V	0.1 A	18
162D10	115/230V 50/60 Hz.	10V C.T.	0.11 A	14
162D20	115/230V 50/60 Hz.	10V	0.11 A	14
164D10	115V 50/60 Hz.	10V C.T.	0.11 A	14
164D20	115V 50/60 Hz.	10V	0.11 A	14
160F10	115/230V 50/60 Hz.	10V C.T.	0.12 A	12
160E20	115/230V 50/60 Hz.	10V	0.12 A	12
161FA10	115V 60 Hz.	10V C.T.	0.12 A	12
161EA20	115V 60 Hz.	10V	0.12 A	12
162E20	115/230V 50/60 Hz.	10V	0.24 A	14
183E20	115/230V 50/60 Hz.	10V	0.24 A	16
164E20	115V 50/60 Hz.	10V	0.24 A	14
162E10	115/230V 50/60 Hz.	10V C.T.	0.25 A	14
183E10	115/230V 50/60 Hz.	10V C.T.	0.25 A	16
229E10	115/230V 50/60 Hz.	10V C.T.	0.25 A	17
229E20	115/230V 50/60 Hz.	10V	0.25 A	17
164E10	115V 50/60 Hz.	10V C.T.	0.25 A	14
187A10	115V 50/60 Hz.	10V C.T.	0.25 A	29
166F10	115V 60 Hz.	10V C.T.	0.3 A	21
160G10	115/230V 50/60 Hz.	10V C.T.	0.44 A	12
160F20	115/230V 50/60 Hz.	10V	0.44 A	12
161GA10	115V 60 Hz.	10V C.T.	0.44 A	12
161FA20	115V 60 Hz.	10V	0.44 A	12
183F10	115/230V 50/60 Hz.	10V C.T.	0.5 A	16
183F20	115/230V 50/60 Hz.	10V	0.5 A	16
227D	115V 60 Hz.	10V	0.5 A	18
166G10	115V 60 Hz.	10V C.T.	0.5 A	21
162F10	115/230V 50/60 Hz.	10V C.T.	0.6 A	14
162F20	115/230V 50/60 Hz.	10V	0.6 A	14
229A10	115/230V 50/60 Hz.	10V C.T.	0.6 A	17
229A20	115/230V 50/60 Hz.	10V	0.6 A	17
186B10	115/230V 50/60 Hz.	10V C.T.	0.6 A	29
164F10	115V 50/60 Hz.	10V C.T.	0.6 A	14
164F20	115V 50/60 Hz.	10V	0.6 A	14
187B10	115V 50/60 Hz.	10V C.T.	0.6 A	29
266F20	117/234V 50/60 Hz.	10V	0.6 A	24
160J10	115/230V 50/60 Hz.	10V C.T.	1.0 A	12
160G20	115/230V 50/60 Hz.	10V	1.0 A	12
183G10	115/230V 50/60 Hz.	10V C.T.	1.0 A	16
183G20	115/230V 50/60 Hz.	10V	1.0 A	16
161J10	115V 60 Hz.	10V C.T.	1.0 A	12
161G20	115V 60 Hz.	10V	1.0 A	12
228D	115V 60 Hz.	10V	1.0 A	18
166J10	115V 60 Hz.	10V C.T.	1.0 A	21
266G20	117/234V 50/60 Hz.	10V	1.0 A	24
162G10	115/230V 50/60 Hz.	10V C.T.	1.2 A	14
162G20	115/230V 50/60 Hz.	10V	1.2 A	14
229B10	115/230V 50/60 Hz.	10V C.T.	1.2 A	17
229B20	115/230V 50/60 Hz.	10V	1.2 A	17
186C10	115/230V 50/60 Hz.	10V C.T.	1.2 A	29
164G10	115V 50/60 Hz.	10V C.T.	1.2 A	14
164G20	115V 50/60 Hz.	10V	1.2 A	14
187C10	115V 50/60 Hz.	10V C.T.	1.2 A	29
226N	115 V 400 Hz.	10V	2.0 A	18
162H10	115/230V 50/60 Hz.	10V C.T.	2.0 A	14
162H20	115/230V 50/60 Hz.	10V	2.0 A	14
183H10	115/230V 50/60 Hz.	10V C.T.	2.0 A	16
183H20	115/230V 50/60 Hz.	10V	2.0 A	16
164H10	115V 50/60 Hz.	10V C.T.	2.0 A	14
164H20	115V 50/60 Hz.	10V	2.0 A	14

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
166L10	115V 60 Hz.	10V C.T.	2.0 A	21
160H10	115/230V 50/60 Hz.	10V C.T.	2.4 A	12
160H20	115/230V 50/60 Hz.	10V	2.4 A	12
229C10	115/230V 50/60 Hz.	10V C.T.	2.4 A	17
229C20	115/230V 50/60 Hz.	10V	2.4 A	17
161H10	115V 60 Hz.	10V C.T.	2.4 A	12
161H20	115V 60 Hz.	10V	2.4 A	12
185C10	115/230V 50/60 Hz.	10V C.T.	2.5 A	33
185C20	115/230V 50/60 Hz.	10V	2.5 A	33
183J10	115/230V 50/60 Hz.	10V C.T.	3.0 A	16
183J20	115/230V 50/60 Hz.	10V	3.0 A	16
186D10	115/230V 50/60 Hz.	10V C.T.	3.0 A	29
187D10	115V 50/60 Hz.	10V C.T.	3.0 A	29
166M10	115V 60 Hz.	10V C.T.	3.0 A	21
162J10	115/230V 50/60 Hz.	10V C.T.	3.6 A	14
162J20	115/230V 50/60 Hz.	10V	3.6 A	14
164J10	115V 50/60 Hz.	10V C.T.	3.6 A	14
164J20	115V 50/60 Hz.	10V	3.6 A	14
227N	115 V 400 Hz.	10V	4.0 A	18
166N10	115V 60 Hz.	10V C.T.	4.0 A	21
167N10	115V 60 Hz.	10V C.T.	4.0 A	31
266L20	117/234V 50/60 Hz.	10V	4.0 A	24
185D10	115/230V 50/60 Hz.	10V C.T.	4.3 A	33
185D20	115/230V 50/60 Hz.	10V	4.4 A	33
229D10	115/230V 50/60 Hz.	10V C.T.	4.8 A	17
229D20	115/230V 50/60 Hz.	10V	4.8 A	17
186E10	115/230V 50/60 Hz.	10V C.T.	5.0 A	29
187E10	115V 50/60 Hz.	10V C.T.	5.0 A	29
166P10	115V 60 Hz.	10V C.T.	5.0 A	21
167P10	115V 60 Hz.	10V C.T.	5.0 A	31
183K10	115/230V 50/60 Hz.	10V C.T.	5.6 A	16
183K20	115/230V 50/60 Hz.	10V	5.6 A	16
266M20	117/234V 50/60 Hz.	10V	6.0 A	24
185E10	115/230V 50/60 Hz.	10V C.T.	8.0 A	33
185E20	115/230V 50/60 Hz.	10V	8.0 A	33
166R10	115V 60 Hz.	10V C.T.	8.0 A	21
167R10	115V 60 Hz.	10V C.T.	8.0 A	31
186F10	115/230V 50/60 Hz.	10V C.T.	10.0 A	29
187F10	115V 50/60 Hz.	10V C.T.	10.0 A	29
166S10	115V 60 Hz.	10V C.T.	10.0 A	21
167S10	115V 60 Hz.	10V C.T.	10.0 A	31
185F10	115/230V 50/60 Hz.	10V C.T.	13.0 A	33
185F20	115/230V 50/60 Hz.	10V	13.0 A	33
185G10	115/230V 50/60 Hz.	10V C.T.	17.5 A	33
185G20	115/230V 50/60 Hz.	10V	17.6 A	33
165V10	115V 60 Hz.	10V C.T.	20.0 A	19
166P11	115V 60 Hz.	11V C.T.	5.0 A	21
167P11	115V 60 Hz.	11V C.T.	5.0 A	31
166S11	115V 60 Hz.	11V C.T.	10.0 A	21
167S11	115V 60 Hz.	11V C.T.	10.0 A	31
165U11	115V 60 Hz.	11V C.T.	15.0 A	19
167U11	115V 60 Hz.	11V C.T.	15.0 A	31
160D24	115/230V 50/60 Hz.	12V	0.07 A	12
161D24	115V 60 Hz.	12V	0.07 A	12
162D24	115/230V 50/60 Hz.	12V	0.09 A	14
164D24	115V 50/60 Hz.	12V	0.09 A	14
160E24	115/230V 50/60 Hz.	12V	0.1 A	12
161E24	115V 60 Hz.	12V	0.1 A	12
166E12	115V 60 Hz.	12V C.T.	0.15 A	21
266E12	117/234V 50/60 Hz.	12V C.T.	0.15 A	24
266C24	117/234V 50/60 Hz.	12V	0.17 A	24
162E24	115/230V 50/60 Hz.	12V	0.2 A	14
183E24	115/230V 50/60 Hz.	12V	0.2 A	16
229E24	115/230V 50/60 Hz.	12V	0.2 A	17
164E24	115V 50/60 Hz.	12V	0.2 A	14
166F12B	115V 60 Hz.	12V C.T.	0.3 A	21
266F12B	117/234V 50/60 Hz.	12V C.T.	0.3 A	24
166F12C	115V 60 Hz.	12V C.T.	0.35 A	21
266F12C	117/234V 50/60 Hz.	12V C.T.	0.35 A	24
160F24	115/230V 50/60 Hz.	12V	0.36 A	12
161F24	115V 60 Hz.	12V	0.36 A	12
266EA24	117/234V 50/60 Hz.	12V	0.4 A	24
183F24	115/230V 50/60 Hz.	12V	0.42 A	16
162F24	115/230V 50/60 Hz.	12V	0.5 A	14
229A24	115/230V 50/60 Hz.	12V	0.5 A	17
164F24	115V 50/60 Hz.	12V	0.5 A	14
266F24	117/234V 50/60 Hz.	12V	0.6 A	24
266GD12	117/234V 50/60 Hz.	12V C.T.	0.7 A	24
166GD12	117V 50/60 Hz.	12V	0.7 A	21
266FB24	117/234V 50/60 Hz.	12V	0.8 A	24
183G24	115/230V 50/60 Hz.	12V	0.8 A	16
160G24	115/230V 50/60 Hz.	12V	0.9 A	12
161G24	115V 60 Hz.	12V	0.9 A	12
162G24	115/230V 50/60 Hz.	12V	1.0 A	14
229B24	115/230V 50/60 Hz.	12V	1.0 A	17
164G24	115V 50/60 Hz.	12V	1.0 A	14
166JA12	115V 60 Hz.	12V C.T.	1.0 A	21
266JA12	117/234V 50/60 Hz.	12V C.T.	1.0 A	24
266G24	117/234V 50/60 Hz.	12V	1.0 A	24
166K12	115V 60 Hz.	12V C.T.	1.2 A	21
266JB12	117/234V 50/60 Hz.	12V C.T.	1.2 A	24
166JB12	117V 50/60 Hz.	12V C.T.	1.2 A	21
182K6	117/234V 50/60 Hz.	12V C.T.	1.25 A	35
182G12	117/234V 50/60 Hz.	12V	1.26 A	35
266GD24	117/234V 50/60 Hz.	12V	1.4 A	24
162H24	115/230V 50/60 Hz.	12V	1.6 A	14
164H24	115V 50/60 Hz.	12V	1.6 A	14
183H24	115/230V 50/60 Hz.	12V	1.66 A	16
160H24	115/230V 50/60 Hz.	12V	2.0 A	12
229C24	115/230V 50/60 Hz.	12V	2.0 A	17

CANADA

Guelph, Ontario (519) 822-2960
 St. Laurent, Quebec (514) 343-9010

USA

Cheektowaga, NY (716) 630-7030

www.hammondmfg.com



A.C. Secondary Voltage - Selection Guide

Power

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
185C24	115/230V 50/60 Hz.	12V	2.0 A	33
161H24	115V 60 Hz.	12V	2.0 A	12
166LA12	115V 60 Hz.	12V C.T.	2.0 A	21
266LA12	117/234V 50/60 Hz.	12V C.T.	2.0 A	24
266J24	117/234V 50/60 Hz.	12V	2.0 A	24
183J24	115/230V 50/60 Hz.	12V	2.5 A	16
182L6	117/234V 50/60 Hz.	12V C.T.	2.5 A	35
182K12	117/234V 50/60 Hz.	12V	2.5 A	35
162J24	115/230V 50/60 Hz.	12V	3.0 A	14
164J24	115V 50/60 Hz.	12V	3.0 A	14
185D24	115/230V 50/60 Hz.	12V	3.6 A	33
229D24	115/230V 50/60 Hz.	12V	4.0 A	17
266N12B	117/234V 50/60 Hz.	12V C.T.	4.0 A	24
266L24	117/234V 50/60 Hz.	12V	4.0 A	24
166N12B	117V 50/60 Hz.	12V C.T.	4.0 A	21
182L12	117/234V 50/60 Hz.	12V	4.16 A	35
182N6	117/234V 50/60 Hz.	12V C.T.	4.17 A	35
183K24	115/230V 50/60 Hz.	12V	4.66 A	16
266PA12	117/234V 50/60 Hz.	12V C.T.	6.0 A	24
266M24	117/234V 50/60 Hz.	12V	6.0 A	24
185E24	115/230V 50/60 Hz.	12V	6.6 A	33
182M12	117/234V 50/60 Hz.	12V	6.66 A	35
182Q6	117/234V 50/60 Hz.	12V C.T.	6.67 A	35
266N24	117/234V 50/60 Hz.	12V	8.0 A	24
266P24	117/234V 50/60 Hz.	12V	10.0 A	24
182P12	117/234V 50/60 Hz.	12V	10.0 A	35
185F24	115/230V 50/60 Hz.	12V	10.8 A	33
266PA24	117/234V 50/60 Hz.	12V	12.0 A	25
182Q12	117/234V 50/60 Hz.	12V	13.34 A	35
185G24	115/230V 50/60 Hz.	12V	14.6 A	33
266R24	117/234V 50/60 Hz.	12V	16.0 A	25
182S12	117/234V 50/60 Hz.	12V	18.76 A	35
266S24	117/234V 50/60 Hz.	12V	20.0 A	25
182T12	117/234V 50/60 Hz.	12V	25.0 A	35
266M25	117/234V 50/60 Hz.	12.5V	6.0 A	25
161C12	115V 60 Hz.	12.6V C.T.	0.04 A	12
166C12	115V 60 Hz.	12.6V C.T.	0.05 A	21
166A24	115V 60 Hz.	12.6V	0.05 A	21
160D12	115/230V 50/60 Hz.	12.6V C.T.	0.07 A	12
161D12	115V 60 Hz.	12.6V C.T.	0.07 A	12
162D12	115/230V 50/60 Hz.	12.6V C.T.	0.09 A	14
164D12	115V 50/60 Hz.	12.6V C.T.	0.09 A	14
160F12	115/230V 50/60 Hz.	12.6V C.T.	0.1 A	12
161FA12	115V 60 Hz.	12.6V C.T.	0.1 A	12
187A12	115V 50/60 Hz.	12.6V C.T.	0.19 A	29
162E12	115/230V 50/60 Hz.	12.6V C.T.	0.2 A	14
183E12	115/230V 50/60 Hz.	12.6V C.T.	0.2 A	16
229E12	115/230V 50/60 Hz.	12.6V C.T.	0.2 A	17
164E12	115V 50/60 Hz.	12.6V C.T.	0.2 A	14
166F12	115V 60 Hz.	12.6V C.T.	0.3 A	21
266F12	117/234V 50/60 Hz.	12.6V C.T.	0.3 A	24
160G12	115/230V 50/60 Hz.	12.6V C.T.	0.35 A	12
161GA12	115V 60 Hz.	12.6V C.T.	0.35 A	12
183F12	115/230V 50/60 Hz.	12.6V C.T.	0.4 A	16
229A12	115/230V 50/60 Hz.	12.6V C.T.	0.45 A	17
162F12	115/230V 50/60 Hz.	12.6V C.T.	0.5 A	14
186B12	115/230V 50/60 Hz.	12.6V C.T.	0.5 A	29
164F12	115V 50/60 Hz.	12.6V C.T.	0.5 A	14
187B12	115V 50/60 Hz.	12.6V C.T.	0.5 A	29
166G12	115V 60 Hz.	12.6V C.T.	0.5 A	21
266G12	117/234V 50/60 Hz.	12.6V C.T.	0.5 A	24
160K12	115/230V 50/60 Hz.	12.6V C.T.	0.8 A	12
183G12	115/230V 50/60 Hz.	12.6V C.T.	0.8 A	16
161K12	115V 60 Hz.	12.6V C.T.	0.8 A	12
229B12	115/230V 50/60 Hz.	12.6V C.T.	0.9 A	17
162G12	115/230V 50/60 Hz.	12.6V C.T.	1.0 A	14
186C12	115/230V 50/60 Hz.	12.6V C.T.	1.0 A	29
164G12	115V 50/60 Hz.	12.6V C.T.	1.0 A	14
187C12	115V 50/60 Hz.	12.6V C.T.	1.0 A	29
166J12	115V 60 Hz.	12.6V C.T.	1.0 A	21
266J12	117/234V 50/60 Hz.	12.6V C.T.	1.0 A	24
266K12	117/234V 50/60 Hz.	12.6V C.T.	1.5 A	24
166K12B	117V 50/60 Hz.	12.6V C.T.	1.5 A	21
162H12	115/230V 50/60 Hz.	12.6V C.T.	1.6 A	14
183H12	115/230V 50/60 Hz.	12.6V C.T.	1.6 A	16
164H12	115V 50/60 Hz.	12.6V C.T.	1.6 A	14
229C12	115/230V 50/60 Hz.	12.6V C.T.	1.9 A	17
160H12	115/230V 50/60 Hz.	12.6V C.T.	2.0 A	12
185C12	115/230V 50/60 Hz.	12.6V C.T.	2.0 A	33
161H12	115V 60 Hz.	12.6V C.T.	2.0 A	12
266L12B	117/234V 50/60 Hz.	12.6V C.T.	2.0 A	24
266J25	117/234V 50/60 Hz.	12.6V	2.0 A	25
166L12B	117V 50/60 Hz.	12.6V C.T.	2.0 A	21
183J12	115/230V 50/60 Hz.	12.6V C.T.	2.4 A	16
186D12	115/230V 50/60 Hz.	12.6V C.T.	2.5 A	29
187D12	115V 50/60 Hz.	12.6V C.T.	2.5 A	29
166L12	115V 60 Hz.	12.6V C.T.	2.5 A	21
167L12	115V 60 Hz.	12.6V C.T.	2.5 A	31
266L12	117/234V 50/60 Hz.	12.6V C.T.	2.5 A	24
162J12	115/230V 50/60 Hz.	12.6V C.T.	2.85 A	14
164J12	115V 50/60 Hz.	12.6V C.T.	2.85 A	14
266M12	117/234V 50/60 Hz.	12.6V C.T.	3.0 A	24
166M12	117V 50/60 Hz.	12.6V C.T.	3.0 A	21
185D12	115/230V 50/60 Hz.	12.6V C.T.	3.4 A	33
229D12	115/230V 50/60 Hz.	12.6V C.T.	3.8 A	17
186E12	115/230V 50/60 Hz.	12.6V C.T.	4.0 A	29
187E12	115V 50/60 Hz.	12.6V C.T.	4.0 A	29
166N12	115V 60 Hz.	12.6V C.T.	4.0 A	21
166N12	115V 60 Hz.	12.6V C.T.	4.0 A	31
266N12	117/234V 50/60 Hz.	12.6V C.T.	4.0 A	24

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
266L25	117/234V 50/60 Hz.	12.6V	4.0 A	25
183K12	115/230V 50/60 Hz.	12.6V C.T.	4.4 A	16
266LH25	117/234V 50/60 Hz.	12.6V	5.6 A	25
166Q12	115V 60 Hz.	12.6V C.T.	6.0 A	21
167Q12	115V 60 Hz.	12.6V C.T.	6.0 A	31
185E12	115/230V 50/60 Hz.	12.6V C.T.	6.3 A	33
186F12	115/230V 50/60 Hz.	12.6V C.T.	8.0 A	29
187F12	115V 50/60 Hz.	12.6V C.T.	8.0 A	29
166R12	115V 60 Hz.	12.6V C.T.	8.0 A	21
167R12	115V 60 Hz.	12.6V C.T.	8.0 A	31
165S12	115V 60 Hz.	12.6V C.T.	10.0 A	19
167S12	115V 60 Hz.	12.6V C.T.	10.0 A	31
185F12	115/230V 50/60 Hz.	12.6V C.T.	10.3 A	33
185G12	115/230V 50/60 Hz.	12.6V C.T.	14.0 A	33
165V12	115V 60 Hz.	12.6V C.T.	20.0 A	19
167V12	115V 60 Hz.	12.6V C.T.	20.0 A	31
226P	115 V 400 Hz.	13V	1.54 A	18
227P	115 V 400 Hz.	13V	3.08 A	18
266J26	117/234V 50/60 Hz.	13.4V	2.0 A	25
160D28	115/230V 50/60 Hz.	14V	0.06 A	12
161D28	115V 60 Hz.	14V	0.06 A	12
160E28	115/230V 50/60 Hz.	14V	0.08 A	12
162D28	115/230V 50/60 Hz.	14V	0.08 A	14
164D28	115V 50/60 Hz.	14V	0.08 A	14
161E28	115V 60 Hz.	14V	0.08 A	12
166E14	115V 60 Hz.	14V C.T.	0.15 A	21
162E28	115/230V 50/60 Hz.	14V	0.17 A	14
164E28	115V 50/60 Hz.	14V	0.17 A	14
183E28	115/230V 50/60 Hz.	14V	0.18 A	16
160F28	115/230V 50/60 Hz.	14V	0.32 A	12
161F28	115V 60 Hz.	14V	0.32 A	12
183F28	115/230V 50/60 Hz.	14V	0.36 A	16
162F28	115/230V 50/60 Hz.	14V	0.4 A	14
164F28	115V 50/60 Hz.	14V	0.4 A	14
166G14	115V 60 Hz.	14V C.T.	0.5 A	21
266G14	117/234V 50/60 Hz.	14V C.T.	0.5 A	24
160G28	115/230V 50/60 Hz.	14V	0.72 A	12
183G28	115/230V 50/60 Hz.	14V	0.72 A	16
161G28	115V 60 Hz.	14V	0.72 A	12
162G28	115/230V 50/60 Hz.	14V	0.84 A	14
164G28	115V 50/60 Hz.	14V	0.84 A	14
166J14	115V 60 Hz.	14V C.T.	1.0 A	21
266J14	117/234V 50/60 Hz.	14V C.T.	1.0 A	24
162H28	115/230V 50/60 Hz.	14V	1.4 A	14
164H28	115V 50/60 Hz.	14V	1.4 A	14
183H28	115/230V 50/60 Hz.	14V	1.44 A	16
160H28	115/230V 50/60 Hz.	14V	1.6 A	12
161H28	115V 60 Hz.	14V	1.6 A	12
185C28	115/230V 50/60 Hz.	14V	1.86 A	33
166L14	115V 60 Hz.	14V C.T.	2.0 A	21
266L14	117/234V 50/60 Hz.	14V C.T.	2.0 A	24
183J28	115/230V 50/60 Hz.	14V	2.12 A	16
162J28	115/230V 50/60 Hz.	14V	2.6 A	14
164J28	115V 50/60 Hz.	14V	2.6 A	14
185D28	115/230V 50/60 Hz.	14V	3.0 A	33
183K28	115/230V 50/60 Hz.	14V	4.0 A	16
167N14	115V 60 Hz.	14V C.T.	4.0 A	31
266L28	117/234V 50/60 Hz.	14V	4.0 A	25
185E28	115/230V 50/60 Hz.	14V	5.6 A	33
166Q14	115V 60 Hz.	14V C.T.	6.0 A	21
167Q14	115V 60 Hz.	14V C.T.	6.0 A	31
266PA14	117/234V 50/60 Hz.	14V C.T.	6.0 A	24
185F28	115/230V 50/60 Hz.	14V	9.2 A	33
185G28	115/230V 50/60 Hz.	14V	12.5 A	33
226F	115V 60 Hz.	15V	0.067 A	18
229E30	115/230V 50/60 Hz.	15V	0.17 A	17
227F	115V 60 Hz.	15V	0.34 A	18
229A30	115/230V 50/60 Hz.	15V	0.4 A	17
228F	115V 60 Hz.	15V	0.67 A	18
229B30	115/230V 50/60 Hz.	15V	0.8 A	17
182G15	117/234V 50/60 Hz.	15V	1.0 A	35
226R	115 V 400 Hz.	15V	1.33 A	18
229C30	115/230V 50/60 Hz.	15V	1.6 A	17
182J15	117/234V 50/60 Hz.	15V	2.0 A	35
227R	115 V 400 Hz.	15V	2.66 A	18
229D30	115/230V 50/60 Hz.	15V	3.2 A	17
182K15	117/234V 50/60 Hz.	15V	3.34 A	35
182M15	117/234V 50/60 Hz.	15V	5.34 A	35
182N15	117/234V 50/60 Hz.	15V	8.0 A	35
182P15	117/234V 50/60 Hz.	15V	10.66 A	35
182H15	117/234V 50/60 Hz.	15V	15.0 A	35
182S15	117/234V 50/60 Hz.	15V	20.0 A	35
161C16	115V 60 Hz.	16V C.T.	0.0313 A	12
160D16	115/230V 50/60 Hz.	16V C.T.	0.055 A	12
161D16	115V 60 Hz.	16V C.T.	0.055 A	12
162D16	115/230V 50/60 Hz.	16V C.T.	0.07 A	14
164D16	115V 50/60 Hz.	16V C.T.	0.07 A	14
160E16	115/230V 50/60 Hz.	16V C.T.	0.075 A	12
161EA16	115V 60 Hz.	16V C.T.	0.075 A	12
162E16	115/230V 50/60 Hz.	16V C.T.	0.15 A	14
183E16	115/230V 50/60 Hz.	16V C.T.	0.15 A	16
229E16	115/230V 50/60 Hz.	16V C.T.	0.15 A	17
164E16	115V 50/60 Hz.	16V C.T.	0.15 A	14
187A16	115V 50/60 Hz.	16V C.T.	0.15 A	29
166F16	115V 60 Hz.	16V C.T.	0.25 A	21
160F16	115/230V 50/60 Hz.	16V C.T.	0.26 A	12
161FA16	115V 60 Hz.	16V C.T.	0.26 A	12
183F16	115/230V 50/60 Hz.	16V C.T.	0.31 A	16
229A16	115/230V 50/60 Hz.	16V C.T.	0.35 A	17
162F16	115/230V 50			

A.C. Secondary Voltage - Selection Guide

Power

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
186B16	115/230V 50/60 Hz.	16V C.T.	0.4 A	29
164F16	115V 50/60 Hz.	16V C.T.	0.4 A	14
187B16	115V 50/60 Hz.	16V C.T.	0.4 A	29
166G16	115V 60 Hz.	16V C.T.	0.5 A	21
266G16	117/234V 50/60 Hz.	16V C.T.	0.5 A	24
183G16	115/230V 50/60 Hz.	16V C.T.	0.62 A	16
160G16	115/230V 50/60 Hz.	16V C.T.	0.64 A	12
161G16	115V 60 Hz.	16V C.T.	0.64 A	12
229B16	115/230V 50/60 Hz.	16V C.T.	0.7 A	17
162G16	115/230V 50/60 Hz.	16V C.T.	0.8 A	14
186C16	115/230V 50/60 Hz.	16V C.T.	0.8 A	29
164G16	115V 50/60 Hz.	16V C.T.	0.8 A	14
187C16	115V 50/60 Hz.	16V C.T.	0.8 A	29
166J16	115V 60 Hz.	16V C.T.	1.0 A	21
266J16	117/234V 50/60 Hz.	16V C.T.	1.0 A	24
162H16	115/230V 50/60 Hz.	16V C.T.	1.25 A	14
183H16	115/230V 50/60 Hz.	16V C.T.	1.25 A	16
164H16	115V 50/60 Hz.	16V C.T.	1.25 A	14
160H16	115/230V 50/60 Hz.	16V C.T.	1.5 A	12
229C16	115/230V 50/60 Hz.	16V C.T.	1.5 A	17
161H16	115V 60 Hz.	16V C.T.	1.5 A	12
185C16	115/230V 50/60 Hz.	16V C.T.	1.6 A	33
183J16	115/230V 50/60 Hz.	16V C.T.	1.9 A	16
186D16	115/230V 50/60 Hz.	16V C.T.	2.0 A	29
187D16	115V 50/60 Hz.	16V C.T.	2.0 A	29
166L16	115V 60 Hz.	16V C.T.	2.2 A	21
266L16	117/234V 50/60 Hz.	16V C.T.	2.2 A	24
162J16	115/230V 50/60 Hz.	16V C.T.	2.25 A	14
164J16	115V 50/60 Hz.	16V C.T.	2.25 A	14
185D16	115/230V 50/60 Hz.	16V C.T.	2.7 A	33
229D16	115/230V 50/60 Hz.	16V C.T.	3.0 A	17
166M16	115V 60 Hz.	16V C.T.	3.0 A	21
167M16	115V 60 Hz.	16V C.T.	3.0 A	31
266M16	117/234V 50/60 Hz.	16V C.T.	3.0 A	24
183K16	115/230V 50/60 Hz.	16V C.T.	3.5 A	16
186E16	115/230V 50/60 Hz.	16V C.T.	3.5 A	29
187E16	115V 50/60 Hz.	16V C.T.	3.5 A	29
185E16	115/230V 50/60 Hz.	16V C.T.	5.0 A	33
167P16	115V 60 Hz.	16V C.T.	5.0 A	31
186F16	115/230V 50/60 Hz.	16V C.T.	6.25 A	29
187F16	115V 50/60 Hz.	16V C.T.	6.25 A	29
185F16	115/230V 50/60 Hz.	16V C.T.	8.1 A	33
185G16	115/230V 50/60 Hz.	16V C.T.	11.0 A	33
160D34	115/230V 50/60 Hz.	17V	0.05 A	12
161D34	115V 60 Hz.	17V	0.05 A	12
160E34	115/230V 50/60 Hz.	17V	0.07 A	12
161E34	115V 60 Hz.	17V	0.07 A	12
229E34	115/230V 50/60 Hz.	17V	0.15 A	17
160F34	115/230V 50/60 Hz.	17V	0.25 A	12
161F34	115V 60 Hz.	17V	0.25 A	12
229A34	115/230V 50/60 Hz.	17V	0.34 A	17
160G34	115/230V 50/60 Hz.	17V	0.6 A	12
161G34	115V 60 Hz.	17V	0.6 A	12
229B34	115/230V 50/60 Hz.	17V	0.68 A	17
160H34	115/230V 50/60 Hz.	17V	1.4 A	12
229C34	115/230V 50/60 Hz.	17V	1.4 A	17
161H34	115V 60 Hz.	17V	1.4 A	12
229D34	115/230V 50/60 Hz.	17V	2.8 A	17
266K35	117/234V 50/60 Hz.	17.5V	3.0 A	25
166B18	115V 60 Hz.	18V C.T.	0.03A	21
162D36	115/230V 50/60 Hz.	18V	0.06 A	14
164D36	115V 50/60 Hz.	18V	0.06 A	14
162E36	115/230V 50/60 Hz.	18V	0.13 A	14
164E36	115V 50/60 Hz.	18V	0.13 A	14
183E36	115/230V 50/60 Hz.	18V	0.14 A	16
183F36	115/230V 50/60 Hz.	18V	0.28 A	16
166E18	115V 60 Hz.	18V C.T.	0.3 A	21
162F36	115/230V 50/60 Hz.	18V	0.34 A	14
164F36	115V 50/60 Hz.	18V	0.34 A	14
183G36	115/230V 50/60 Hz.	18V	0.56 A	16
162G36	115/230V 50/60 Hz.	18V	0.7 A	14
164G36	115V 50/60 Hz.	18V	0.7 A	14
182H9	117/234V 50/60 Hz.	18V C.T.	0.83 A	35
182F18	117/234V 50/60 Hz.	18V	0.84 A	35
266G36	117/234V 50/60 Hz.	18V	1.0 A	25
162H36	115/230V 50/60 Hz.	18V	1.1 A	14
164H36	115V 50/60 Hz.	18V	1.1 A	14
183H36	115/230V 50/60 Hz.	18V	1.12 A	16
185C36	115/230V 50/60 Hz.	18V	1.4 A	33
166K18	115V 60 Hz.	18V C.T.	1.5 A	21
266K18	117/234V 50/60 Hz.	18V C.T.	1.5 A	24
183J36	115/230V 50/60 Hz.	18V	1.64 A	16
182H18	117/234V 50/60 Hz.	18V	1.66 A	35
182K9	117/234V 50/60 Hz.	18V C.T.	1.67 A	35
162J36	115/230V 50/60 Hz.	18V	2.0 A	14
164J36	115V 50/60 Hz.	18V	2.0 A	14
266J36	117/234V 50/60 Hz.	18V	2.0 A	25
185D36	115/230V 50/60 Hz.	18V	2.4 A	33
182M9	117/234V 50/60 Hz.	18V C.T.	2.78 A	35
182J18	117/234V 50/60 Hz.	18V	2.78 A	35
166M18	115V 60 Hz.	18V C.T.	3.0 A	21
167M18	115V 60 Hz.	18V C.T.	3.0 A	31
266M18	117/234V 50/60 Hz.	18V C.T.	3.0 A	24
183K36	115/230V 50/60 Hz.	18V	3.12 A	16
185E36	115/230V 50/60 Hz.	18V	4.4 A	33
182N9	117/234V 50/60 Hz.	18V C.T.	4.44 A	35
182L18	117/234V 50/60 Hz.	18V	4.44 A	35
166P18	115V 60 Hz.	18V C.T.	5.0 A	21
167P18	115V 60 Hz.	18V C.T.	5.0 A	31
266P18	117/234V 50/60 Hz.	18V C.T.	5.0 A	24

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
182M18	117/234V 50/60 Hz.	18V	6.66 A	35
182Q9	117/234V 50/60 Hz.	18V C.T.	6.67 A	35
185F36	115/230V 50/60 Hz.	18V	7.2 A	33
182N18	117/234V 50/60 Hz.	18V	8.88 A	35
185G36	115/230V 50/60 Hz.	18V	9.6 A	33
165S18	115V 60 Hz.	18V C.T.	10.0 A	19
187S18	115V 60 Hz.	18V C.T.	10.0 A	31
182G18	117/234V 50/60 Hz.	18V	12.5 A	35
165U18	115V 60 Hz.	18V C.T.	15.0 A	19
167U18	115V 60 Hz.	18V C.T.	15.0 A	31
165V18	115V 60 Hz.	18V C.T.	20.0 A	19
167V18	115V 60 Hz.	18V C.T.	20.0 A	31
160D40	115/230V 50/60 Hz.	20V	0.04 A	12
161D40	115V 60 Hz.	20V	0.04 A	12
160D20	115/230V 50/60 Hz.	20V C.T.	0.045 A	12
161D20	115V 60 Hz.	20V C.T.	0.045 A	12
226D	115V 60 Hz.	20V C.T.	0.05 A	18
226H	115V 60 Hz.	20V	0.05 A	18
162D20	115/230V 50/60 Hz.	20V C.T.	0.055 A	14
164D20	115V 50/60 Hz.	20V C.T.	0.055 A	14
160E20	115/230V 50/60 Hz.	20V C.T.	0.06 A	12
160E40	115/230V 50/60 Hz.	20V	0.06 A	12
161EA20	115V 60 Hz.	20V C.T.	0.06 A	12
161E40	115V 60 Hz.	20V	0.06 A	12
166D20	115V 60 Hz.	20V C.T.	0.1 A	21
162E20	115/230V 50/60 Hz.	20V C.T.	0.12 A	14
183E20	115/230V 50/60 Hz.	20V C.T.	0.12 A	16
229E40	115/230V 50/60 Hz.	20V	0.12 A	17
164E20	115V 50/60 Hz.	20V C.T.	0.12 A	14
187A20	115V 50/60 Hz.	20V C.T.	0.12 A	29
229E20	115/230V 50/60 Hz.	20V C.T.	0.125 A	17
166E20	115V 60 Hz.	20V C.T.	0.15 A	21
160F20	115/230V 50/60 Hz.	20V C.T.	0.22 A	12
160F40	115/230V 50/60 Hz.	20V	0.22 A	12
161FA20	115V 60 Hz.	20V C.T.	0.22 A	12
161F40	115V 60 Hz.	20V	0.22 A	12
183F20	115/230V 50/60 Hz.	20V C.T.	0.25 A	16
227D	115V 60 Hz.	20V C.T.	0.25 A	18
227H	115V 60 Hz.	20V	0.25 A	18
162F20	115/230V 50/60 Hz.	20V C.T.	0.3 A	14
229A20	115/230V 50/60 Hz.	20V C.T.	0.3 A	17
229A40	115/230V 50/60 Hz.	20V	0.3 A	17
186B20	115/230V 50/60 Hz.	20V C.T.	0.3 A	29
164F20	115V 50/60 Hz.	20V C.T.	0.3 A	14
187B20	115V 50/60 Hz.	20V C.T.	0.3 A	29
166F20	115V 60 Hz.	20V C.T.	0.3 A	21
266F20	117/234V 50/60 Hz.	20V C.T.	0.3 A	24
160G20	115/230V 50/60 Hz.	20V C.T.	0.5 A	12
160G40	115/230V 50/60 Hz.	20V	0.5 A	12
183G20	115/230V 50/60 Hz.	20V C.T.	0.5 A	16
161G20	115V 60 Hz.	20V C.T.	0.5 A	12
161G40	115V 60 Hz.	20V	0.5 A	12
228D	115V 60 Hz.	20V C.T.	0.5 A	18
228H	115V 60 Hz.	20V	0.5 A	18
166G20	115V 60 Hz.	20V C.T.	0.5 A	21
266G20	117/234V 50/60 Hz.	20V C.T.	0.5 A	24
162G20	115/230V 50/60 Hz.	20V C.T.	0.6 A	14
229B20	115/230V 50/60 Hz.	20V C.T.	0.6 A	17
229B40	115/230V 50/60 Hz.	20V	0.6 A	17
186C20	115/230V 50/60 Hz.	20V C.T.	0.6 A	29
164G20	115V 50/60 Hz.	20V C.T.	0.6 A	14
187C20	115V 50/60 Hz.	20V C.T.	0.6 A	29
226N	115 V 400 Hz.	20V C.T.	1.0 A	18
226T	115 V 400 Hz.	20V	1.0 A	18
162H20	115/230V 50/60 Hz.	20V C.T.	1.0 A	14
183H20	115/230V 50/60 Hz.	20V C.T.	1.0 A	16
164H20	115V 50/60 Hz.	20V C.T.	1.0 A	14
166J20	115V 60 Hz.	20V C.T.	1.0 A	21
160H20	115/230V 50/60 Hz.	20V C.T.	1.2 A	12
160H40	115/230V 50/60 Hz.	20V	1.2 A	12
229C20	115/230V 50/60 Hz.	20V C.T.	1.2 A	17
229C40	115/230V 50/60 Hz.	20V	1.2 A	17
161H20	115V 60 Hz.	20V C.T.	1.2 A	12
161H40	115V 60 Hz.	20V	1.2 A	12
185C20	115/230V 50/60 Hz.	20V C.T.	1.25 A	33
183J20	115/230V 50/60 Hz.	20V C.T.	1.5 A	16
186D20	115/230V 50/60 Hz.	20V C.T.	1.5 A	29
187D20	115V 50/60 Hz.	20V C.T.	1.5 A	29
162J20	115/230V 50/60 Hz.	20V C.T.	1.8 A	14
164J20	115V 50/60 Hz.	20V C.T.	1.8 A	14
227N	115 V 400 Hz.	20V C.T.	2.0 A	18
227T	115 V 400 Hz.	20V	2.0 A	18
166L20	115V 60 Hz.	20V C.T.	2.0 A	21
266L20	117/234V 50/60 Hz.	20V C.T.	2.0 A	24
185D20	115/230V 50/60 Hz.	20V C.T.	2.2 A	33
229D20	115/230V 50/60 Hz.	20V C.T.	2.4 A	17
229D40	115/230V 50/60 Hz.	20V	2.4 A	17
183K20	115/230V 50/60 Hz.	20V C.T.	2.8 A	16
186E20	115/230V 50/60 Hz.	20V C.T.	2.8 A	29
187E20	115V 50/60 Hz.	20V C.T.	2.8 A	29
167M20	115V 60 Hz.	20V C.T.	3.0 A	31
266M20	117/234V 50/60 Hz.	20V C.T.	3.0 A	24
185E20	115/230V 50/60 Hz.	20V C.T.	4.0 A	33
186F20	115/230V 50/60 Hz.	20V C.T.	5.0 A	29
187F20	115V 50/60 Hz.	20V C.T.	5.0 A	29
167P20	115V 60 Hz.	20V C.T.	5.0 A	31
185F20	115/230V 50/60 Hz.	20V C.T.	6.5 A	33
185G20	115/230V 50/60 Hz.	20V C.T.	8.8 A	33
167U20	115V 60 Hz.	20V C.T.	16.0 A	31
182F22	117/234V 50/60 Hz.	22V	0.68 A	35

CANADA

Guelph, Ontario (519) 822-2960
 St. Laurent, Quebec (514) 343-9010

USA

Cheektowaga, NY (716)

A.C. Secondary Voltage - Selection Guide

Power

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
182G22	117/234V 50/60 Hz.	22V	1.36 A	35
166L22	115V 60 Hz.	22V C.T.	2.0 A	21
182J22	117/234V 50/60 Hz.	22V	2.28 A	35
182L22	117/234V 50/60 Hz.	22V	3.64 A	35
182M22	117/234V 50/60 Hz.	22V	5.46 A	35
182N22	117/234V 50/60 Hz.	22V	7.28 A	35
182P22	117/234V 50/60 Hz.	22V	10.22 A	35
165T22	115V 60 Hz.	22V C.T.	12.0 A	19
167T22	115V 60 Hz.	22V C.T.	12.0 A	31
165V22	115V 60 Hz.	22V C.T.	20.0 A	19
167V22	115V 60 Hz.	22V C.T.	20.0 A	31
160D24	115/230V 50/60 Hz.	24V C.T.	0.035 A	12
161D24	115V 60 Hz.	24V C.T.	0.035 A	12
162D24	115/230V 50/60 Hz.	24V C.T.	0.045 A	14
164D24	115V 50/60 Hz.	24V C.T.	0.045 A	14
162D48	115/230V 50/60 Hz.	24V	0.046 A	14
164D48	115V 50/60 Hz.	24V	0.046 A	14
160E24	115/230V 50/60 Hz.	24V C.T.	0.05 A	12
161E24	115V 60 Hz.	24V C.T.	0.05 A	12
166C24	115V 60 Hz.	24V C.T.	0.085 A	21
266C24	117/234V 50/60 Hz.	24V C.T.	0.085 A	24
162E24	115/230V 50/60 Hz.	24V C.T.	0.1 A	14
162E48	115/230V 50/60 Hz.	24V	0.1 A	14
183E24	115/230V 50/60 Hz.	24V C.T.	0.1 A	16
229E24	115/230V 50/60 Hz.	24V C.T.	0.1 A	17
164E24	115V 50/60 Hz.	24V C.T.	0.1 A	14
164E48	115V 50/60 Hz.	24V	0.1 A	14
187A24	115V 50/60 Hz.	24V C.T.	0.1 A	29
160F24	115/230V 50/60 Hz.	24V C.T.	0.18 A	12
161F24	115V 60 Hz.	24V C.T.	0.18 A	12
166EA24	115V 60 Hz.	24V C.T.	0.2 A	21
266EA24	117/234V 50/60 Hz.	24V C.T.	0.2 A	24
183F24	115/230V 50/60 Hz.	24V C.T.	0.21 A	16
162F24	115/230V 50/60 Hz.	24V C.T.	0.25 A	14
162F48	115/230V 50/60 Hz.	24V	0.25 A	14
229A24	115/230V 50/60 Hz.	24V C.T.	0.25 A	17
186B24	115/230V 50/60 Hz.	24V C.T.	0.25 A	29
164F24	115V 50/60 Hz.	24V C.T.	0.25 A	14
164F48	115V 50/60 Hz.	24V	0.25 A	14
187B24	115V 50/60 Hz.	24V C.T.	0.25 A	29
266F24	117/234V 50/60 Hz.	24V C.T.	0.3 A	24
266FB24	117/234V 50/60 Hz.	24V C.T.	0.4 A	24
166FB24	117V 50/60 Hz.	24V C.T.	0.4 A	21
183G24	115/230V 50/60 Hz.	24V C.T.	0.42 A	16
160G24	115/230V 50/60 Hz.	24V C.T.	0.45 A	12
161G24	115V 60 Hz.	24V C.T.	0.45 A	12
162G24	115/230V 50/60 Hz.	24V C.T.	0.5 A	14
162G48	115/230V 50/60 Hz.	24V	0.5 A	14
229B24	115/230V 50/60 Hz.	24V C.T.	0.5 A	17
186C24	115/230V 50/60 Hz.	24V C.T.	0.5 A	29
164G24	115V 50/60 Hz.	24V C.T.	0.5 A	14
164G48	115V 50/60 Hz.	24V	0.5 A	14
187C24	115V 50/60 Hz.	24V C.T.	0.5 A	29
266G24	117/234V 50/60 Hz.	24V C.T.	0.5 A	24
182G12	117/234V 50/60 Hz.	24V C.T.	0.63 A	35
266GD24	117/234V 50/60 Hz.	24V C.T.	0.7 A	24
166GD24B	117V 50/60 Hz.	24V C.T.	0.7 A	21
162H24	115/230V 50/60 Hz.	24V C.T.	0.8 A	14
162H48	115/230V 50/60 Hz.	24V	0.8 A	14
164H24	115V 50/60 Hz.	24V C.T.	0.8 A	14
164H48	115V 50/60 Hz.	24V	0.8 A	14
183H24	115/230V 50/60 Hz.	24V C.T.	0.83 A	16
160H24	115/230V 50/60 Hz.	24V C.T.	1.0 A	12
229C24	115/230V 50/60 Hz.	24V C.T.	1.0 A	17
185C24	115/230V 50/60 Hz.	24V C.T.	1.0 A	33
161H24	115V 60 Hz.	24V C.T.	1.0 A	12
166JB24	115V 60 Hz.	24V C.T.	1.0 A	21
266J24	117/234V 50/60 Hz.	24V C.T.	1.0 A	24
166J24	117V 50/60 Hz.	24V C.T.	1.0 A	21
PHC25JGA	120V 60 Hz.	24V	1.04 A	26
PHC25LGA	208V 60 Hz.	24V	1.04 A	26
PHC25KGA	347V 60 Hz.	24V	1.04 A	26
PHC25AGA	600V 60 Hz.	24V	1.04 A	26
183J24	115/230V 50/60 Hz.	24V C.T.	1.25 A	16
186D24	115/230V 50/60 Hz.	24V C.T.	1.25 A	29
187D24	115V 50/60 Hz.	24V C.T.	1.25 A	29
182K12	117/234V 50/60 Hz.	24V C.T.	1.25 A	35
162J24	115/230V 50/60 Hz.	24V C.T.	1.5 A	14
162J48	115/230V 50/60 Hz.	24V	1.5 A	14
164J24	115V 50/60 Hz.	24V C.T.	1.5 A	14
164J48	115V 50/60 Hz.	24V	1.5 A	14
185D24	115/230V 50/60 Hz.	24V C.T.	1.8 A	33
229D24	115/230V 50/60 Hz.	24V C.T.	2.0 A	17
166L24	115V 60 Hz.	24V C.T.	2.0 A	21
167L24	115V 60 Hz.	24V C.T.	2.0 A	31
266L24	117/234V 50/60 Hz.	24V C.T.	2.0 A	24
266J48	117/234V 50/60 Hz.	24V	2.0 A	25
182L12	117/234V 50/60 Hz.	24V C.T.	2.08 A	35
PHC50JGA	120V 60 Hz.	24V	2.08 A	26
PHC50LGA	208V 60 Hz.	24V	2.08 A	26
PHC50KGA	347V 60 Hz.	24V	2.08 A	26
PHC50AGA	600V 60 Hz.	24V	2.08 A	26
183K24	115/230V 50/60 Hz.	24V C.T.	2.33 A	16
186E24	115/230V 50/60 Hz.	24V C.T.	2.4 A	29
187E24	115V 50/60 Hz.	24V C.T.	2.4 A	29
166M24	115V 60 Hz.	24V C.T.	3.0 A	21
266M24	117/234V 50/60 Hz.	24V C.T.	3.0 A	24
185E24	115/230V 50/60 Hz.	24V C.T.	3.3 A	33
182M12	117/234V 50/60 Hz.	24V C.T.	3.33 A	35
186F24	115/230V 50/60 Hz.	24V C.T.	4.0 A	29

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
187F24	115V 50/60 Hz.	24V C.T.	4.0 A	29
166N24	115V 60 Hz.	24V C.T.	4.0 A	21
266N24	117/234V 50/60 Hz.	24V C.T.	4.0 A	24
266L48	117/234V 50/60 Hz.	24V	4.0 A	25
266P24	117/234V 50/60 Hz.	24V C.T.	5.0 A	24
182P12	117/234V 50/60 Hz.	24V C.T.	5.0 A	35
185F24	115/230V 50/60 Hz.	24V C.T.	5.4 A	33
266PA24	117/234V 50/60 Hz.	24V C.T.	6.0 A	25
266M48	117/234V 50/60 Hz.	24V	6.0 A	25
182Q12	117/234V 50/60 Hz.	24V C.T.	6.67 A	35
185G24	115/230V 50/60 Hz.	24V C.T.	7.3 A	33
266R24	117/234V 50/60 Hz.	24V C.T.	8.0 A	25
266N48	117/234V 50/60 Hz.	24V	8.0 A	25
182S12	117/234V 50/60 Hz.	24V C.T.	9.38 A	35
266S24	117/234V 50/60 Hz.	24V C.T.	10.0 A	25
182T12	117/234V 50/60 Hz.	24V C.T.	12.5 A	35
182S24	117/234V 50/60 Hz.	24V	20.82 A	35
182T24	117/234V 50/60 Hz.	24V	26.04 A	35
182U24	117/234V 50/60 Hz.	24V	31.26 A	35
182V24	117/234V 50/60 Hz.	24V	41.7 A	35
166D25	115V 60 Hz.	25V C.T.	0.1 A	21
166E25	115V 60 Hz.	25V C.T.	0.15 A	21
166F25	115V 60 Hz.	25V C.T.	0.3 A	21
166G25	115V 60 Hz.	25V C.T.	0.5 A	21
166J25	115V 60 Hz.	25V C.T.	1.0 A	21
167J25	115V 60 Hz.	25V C.T.	1.0 A	31
166J25B	117V 50/60 Hz.	25V C.T.	1.0 A	21
166K25	115V 60 Hz.	25V C.T.	1.5 A	21
167K25	115V 60 Hz.	25V C.T.	1.5 A	31
166L25	115V 60 Hz.	25V C.T.	2.0 A	21
166M25	115V 60 Hz.	25V C.T.	3.0 A	21
167M25	115V 60 Hz.	25V C.T.	3.0 A	31
266M25	117/234V 50/60 Hz.	25V C.T.	3.0 A	25
167N25	115V 60 Hz.	25V C.T.	4.0 A	31
165P25	115V 60 Hz.	25V C.T.	5.0 A	19
167P25	115V 60 Hz.	25V C.T.	5.0 A	31
165S25	115V 60 Hz.	25V C.T.	10.0 A	19
167S25	115V 60 Hz.	25V C.T.	10.0 A	31
166A24	115V 60 Hz.	25.2V C.T.	0.025 A	21
266J25	117/234V 50/60 Hz.	25.2V C.T.	1.0 A	25
166L25B	115V 50/60 Hz.	25.2V C.T.	2.0 A	21
266L25	117/234V 50/60 Hz.	25.2V C.T.	2.0 A	25
266LH25	117/234V 50/60 Hz.	25.2V C.T.	2.8 A	25
226P	115 V 400 Hz.	26V C.T.	0.77 A	18
227P	115 V 400 Hz.	26V C.T.	1.54 A	18
266J26	117/234V 50/60 Hz.	26.8V C.T.	1.0 A	25
160D28	115/230V 50/60 Hz.	28V C.T.	0.03 A	12
160D56	115/230V 50/60 Hz.	28V	0.03 A	12
161D28	115V 60 Hz.	28V C.T.	0.03 A	12
161D56	115V 60 Hz.	28V	0.03 A	12
160E28	115/230V 50/60 Hz.	28V C.T.	0.04 A	12
160E56	115/230V 50/60 Hz.	28V	0.04 A	12
162D28	115/230V 50/60 Hz.	28V C.T.	0.04 A	14
162D56	115/230V 50/60 Hz.	28V	0.04 A	14
164D28	115V 50/60 Hz.	28V C.T.	0.04 A	14
164D56	115V 50/60 Hz.	28V	0.04 A	14
161E28	115V 60 Hz.	28V C.T.	0.04 A	12
161E56	115V 60 Hz.	28V	0.04 A	12
187A28	115V 50/60 Hz.	28V C.T.	0.08 A	29
162E28	115/230V 50/60 Hz.	28V C.T.	0.085 A	14
164E28	115V 50/60 Hz.	28V C.T.	0.085 A	14
162E56	115/230V 50/60 Hz.	28V	0.09 A	14
183E28	115/230V 50/60 Hz.	28V C.T.	0.09 A	16
229E56	115/230V 50/60 Hz.	28V	0.09 A	17
164E56	115V 50/60 Hz.	28V	0.09 A	14
160F28	115/230V 50/60 Hz.	28V C.T.	0.16 A	12
160F56	115/230V 50/60 Hz.	28V	0.16 A	12
161F28	115V 60 Hz.	28V C.T.	0.16 A	12
161F56	115V 60 Hz.	28V	0.16 A	12
183F28	115/230V 50/60 Hz.	28V C.T.	0.18 A	16
162F28	115/230V 50/60 Hz.	28V C.T.	0.2 A	14
229A56	115/230V 50/60 Hz.	28V	0.2 A	17
186B28	115/230V 50/60 Hz.	28V C.T.	0.2 A	29
164F28	115V 50/60 Hz.	28V C.T.	0.2 A	14
187B28	115V 50/60 Hz.	28V C.T.	0.2 A	29
162F56	115/230V 50/60 Hz.	28V	0.22 A	14
164F56	115V 50/60 Hz.	28V	0.22 A	14
166F28	115V 60 Hz.	28V C.T.	0.25 A	21
160G28	115/230V 50/60 Hz.	28V C.T.	0.36 A	12
160G56	115/230V 50/60 Hz.	28V	0.36 A	12
183G28	115/230V 50/60 Hz.	28V C.T.	0.36 A	16
161G28	115V 60 Hz.	28V C.T.	0.36 A	12
161G56	115V 60 Hz.	28V	0.36 A	12
229B56	115/230V 50/60 Hz.	28V	0.4 A	17
162G28	115/230V 50/60 Hz.	28V C.T.	0.42 A	14
186C28	115/230V 50/60 Hz.	28V C.T.	0.42 A	29
164G28	115V 50/60 Hz.	28V C.T.	0.42 A	14
187C28	115V 50/60 Hz.	28V C.T.	0.42 A	29
162G56	115/230V 50/60 Hz.	28V	0.44 A	14
164G56	115V 50/60 Hz.	28V	0.44 A	14
166G28	115V 60 Hz.	28V C.T.	0.5 A	21
162H28	115/230V 50/60 Hz.	28V C.T.	0.7 A	14
162H56	115/230V 50/60 Hz.	28V	0.7 A	14
164H28	115V 50/60 Hz.	28V C.T.	0.7 A	14
164H56	115V 50/60 Hz.	28V	0.7 A	14
183H28	115/230V 50/60 Hz.	28V C.T.	0.72 A	16
160H28	115/230V 50/60 Hz.	28V C.T.	0.8 A	12
161H28	115V 60 Hz.	28V C.T.	0.8 A	12
160H56	115/230V 50/60 Hz.	28V	0.84 A	12
161H56	115V 60 Hz.	28V	0.84 A	12

EUROPE

Basingstoke, UK 01256 812812

A.C. Secondary Voltage - Selection Guide

Power

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
229C56	115/230V 50/60 Hz.	28V	0.85 A	17
185C28	115/230V 50/60 Hz.	28V C.T.	0.9 A	33
166J28	115V 60 Hz.	28V C.T.	1.0 A	22
167J28	115V 60 Hz.	28V C.T.	1.0 A	31
183J28	115/230V 50/60 Hz.	28V C.T.	1.06 A	16
186D28	115/230V 50/60 Hz.	28V C.T.	1.07 A	29
187D28	115V 50/60 Hz.	28V C.T.	1.07 A	29
162J28	115/230V 50/60 Hz.	28V C.T.	1.3 A	14
162J56	115/230V 50/60 Hz.	28V	1.3 A	14
164J28	115V 50/60 Hz.	28V C.T.	1.3 A	14
164J56	115V 50/60 Hz.	28V	1.3 A	14
185D28	115/230V 50/60 Hz.	28V C.T.	1.5 A	33
229D56	115/230V 50/60 Hz.	28V	1.7 A	17
183K28	115/230V 50/60 Hz.	28V C.T.	2.0 A	16
186E28	115/230V 50/60 Hz.	28V C.T.	2.0 A	29
187E28	115V 50/60 Hz.	28V C.T.	2.0 A	29
166L28	115V 60 Hz.	28V C.T.	2.0 A	22
167L28	115V 60 Hz.	28V C.T.	2.0 A	31
266L28	117/234V 50/60 Hz.	28V C.T.	2.0 A	25
185E28	115/230V 50/60 Hz.	28V C.T.	2.8 A	33
167M28	115V 60 Hz.	28V C.T.	3.0 A	31
186F28	115/230V 50/60 Hz.	28V C.T.	3.57 A	29
187F28	115V 50/60 Hz.	28V C.T.	3.57 A	29
185F28	115/230V 50/60 Hz.	28V C.T.	4.6 A	33
185G28	115/230V 50/60 Hz.	28V C.T.	6.25 A	33
226F	115V 60 Hz.	30V C.T.	0.034 A	18
229E30	115/230V 50/60 Hz.	30V C.T.	0.085 A	17
166E30	115V 60 Hz.	30V C.T.	0.15 A	22
227F	115V 60 Hz.	30V C.T.	0.17 A	18
229A30	115/230V 50/60 Hz.	30V C.T.	0.2 A	17
166F30	115V 60 Hz.	30V C.T.	0.25 A	22
228F	115V 60 Hz.	30V C.T.	0.34 A	18
229B30	115/230V 50/60 Hz.	30V C.T.	0.4 A	17
166G30	115V 60 Hz.	30V C.T.	0.5 A	22
182G15	117/234V 50/60 Hz.	30V C.T.	0.5 A	35
226R	115 V 400 Hz.	30V C.T.	0.67 A	18
229C30	115/230V 50/60 Hz.	30V C.T.	0.8 A	17
182J15	117/234V 50/60 Hz.	30V C.T.	1.0 A	35
227R	115 V 400 Hz.	30V C.T.	1.33 A	18
167K30	115V 60 Hz.	30V C.T.	1.5 A	31
229D30	115/230V 50/60 Hz.	30V C.T.	1.6 A	17
182K15	117/234V 50/60 Hz.	30V C.T.	1.67 A	35
182K30	117/234V 50/60 Hz.	30V	2.66 A	35
182M15	117/234V 50/60 Hz.	30V C.T.	2.67 A	35
167M30	115V 60 Hz.	30V C.T.	3.0 A	31
182N15	117/234V 50/60 Hz.	30V C.T.	4.0 A	35
182L30	117/234V 50/60 Hz.	30V	4.0 A	35
165P30	115V 60 Hz.	30V C.T.	5.0 A	19
167P30	115V 60 Hz.	30V C.T.	5.0 A	31
182P15	117/234V 50/60 Hz.	30V C.T.	5.33 A	35
182M30	117/234V 50/60 Hz.	30V	5.34 A	35
182H15	117/234V 50/60 Hz.	30V C.T.	7.5 A	35
182F30	117/234V 50/60 Hz.	30V	7.5 A	35
165S30	115V 60 Hz.	30V C.T.	10.0 A	19
167S30	115V 60 Hz.	30V C.T.	10.0 A	31
182S15	117/234V 50/60 Hz.	30V C.T.	10.0 A	35
182P30	117/234V 50/60 Hz.	30V	10.0 A	35
182R30	117/234V 50/60 Hz.	30V	16.66 A	35
182S30	117/234V 50/60 Hz.	30V	20.84 A	35
182T30	117/234V 50/60 Hz.	30V	25.0 A	35
182U30	117/234V 50/60 Hz.	30V	33.3 A	35
166J33	115V 60 Hz.	33V C.T.	1.0 A	22
167J33	115V 60 Hz.	33V C.T.	1.0 A	31
160D34	115/230V 50/60 Hz.	34V C.T.	0.025 A	12
161D34	115V 60 Hz.	34V C.T.	0.025 A	12
160E34	115/230V 50/60 Hz.	34V C.T.	0.035 A	12
161E34	115V 60 Hz.	34V C.T.	0.035 A	12
229E34	115/230V 50/60 Hz.	34V C.T.	0.075 A	17
160F34	115/230V 50/60 Hz.	34V C.T.	0.125 A	12
161F34	115V 60 Hz.	34V C.T.	0.125 A	12
229A34	115/230V 50/60 Hz.	34V C.T.	0.17 A	17
160G34	115/230V 50/60 Hz.	34V C.T.	0.3 A	12
161G34	115V 60 Hz.	34V C.T.	0.3 A	12
229B34	115/230V 50/60 Hz.	34V C.T.	0.34 A	17
160H34	115/230V 50/60 Hz.	34V C.T.	0.7 A	12
229C34	115/230V 50/60 Hz.	34V C.T.	0.7 A	17
161H34	115V 60 Hz.	34V C.T.	0.7 A	12
229D34	115/230V 50/60 Hz.	34V C.T.	1.4 A	17
166K35	115V 60 Hz.	35V C.T.	1.5 A	22
266K35	117/234V 50/60 Hz.	35V C.T.	1.5 A	25
162D36	115/230V 50/60 Hz.	36V C.T.	0.03 A	14
164D36	115V 50/60 Hz.	36V C.T.	0.03 A	14
187A36	115V 50/60 Hz.	36V C.T.	0.06 A	29
162E36	115/230V 50/60 Hz.	36V C.T.	0.065 A	14
164E36	115V 50/60 Hz.	36V C.T.	0.065 A	14
183E36	115/230V 50/60 Hz.	36V C.T.	0.07 A	16
183F36	115/230V 50/60 Hz.	36V C.T.	0.14 A	22
166E36	115V 60 Hz.	36V C.T.	0.15 A	16
162F36	115/230V 50/60 Hz.	36V C.T.	0.17 A	14
186B36	115/230V 50/60 Hz.	36V C.T.	0.17 A	29
164F36	115V 50/60 Hz.	36V C.T.	0.17 A	14
187B36	115V 50/60 Hz.	36V C.T.	0.17 A	29
183G36	115/230V 50/60 Hz.	36V C.T.	0.28 A	16
166F36	115V 60 Hz.	36V C.T.	0.3 A	22
162G36	115/230V 50/60 Hz.	36V C.T.	0.35 A	14
186C36	115/230V 50/60 Hz.	36V C.T.	0.35 A	29
164G36	115V 50/60 Hz.	36V C.T.	0.35 A	14
187C36	115V 50/60 Hz.	36V C.T.	0.35 A	29
182F18	117/234V 50/60 Hz.	36V C.T.	0.42 A	35
166G36	115V 60 Hz.	36V C.T.	0.5 A	22

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
266G36	117/234V 50/60 Hz.	36V C.T.	0.5 A	25
162H36	115/230V 50/60 Hz.	36V C.T.	0.55 A	14
164H36	115V 50/60 Hz.	36V C.T.	0.55 A	14
183H36	115/230V 50/60 Hz.	36V C.T.	0.56 A	16
185C36	115/230V 50/60 Hz.	36V C.T.	0.7 A	33
183J36	115/230V 50/60 Hz.	36V C.T.	0.82 A	16
182H18	117/234V 50/60 Hz.	36V C.T.	0.83 A	35
186D36	115/230V 50/60 Hz.	36V C.T.	0.85 A	29
187D36	115V 50/60 Hz.	36V C.T.	0.85 A	29
162J36	115/230V 50/60 Hz.	36V C.T.	1.0 A	14
164J36	115V 50/60 Hz.	36V C.T.	1.0 A	14
166J36	115V 60 Hz.	36V C.T.	1.0 A	22
167J36	115V 60 Hz.	36V C.T.	1.0 A	31
266J36	117/234V 50/60 Hz.	36V C.T.	1.0 A	25
185D36	115/230V 50/60 Hz.	36V C.T.	1.2 A	33
182J18	117/234V 50/60 Hz.	36V C.T.	1.39 A	35
186E36	115/230V 50/60 Hz.	36V C.T.	1.5 A	29
187E36	115V 50/60 Hz.	36V C.T.	1.5 A	29
183K36	115/230V 50/60 Hz.	36V C.T.	1.56 A	16
167L36	115V 60 Hz.	36V C.T.	2.0 A	31
185E36	115/230V 50/60 Hz.	36V C.T.	2.2 A	33
182L18	117/234V 50/60 Hz.	36V C.T.	2.22 A	35
186F36	115/230V 50/60 Hz.	36V C.T.	2.8 A	29
187F36	115V 50/60 Hz.	36V C.T.	2.8 A	29
167M36	115V 60 Hz.	36V C.T.	3.0 A	31
182M18	117/234V 50/60 Hz.	36V C.T.	3.33 A	35
185F36	115/230V 50/60 Hz.	36V C.T.	3.6 A	33
182N18	117/234V 50/60 Hz.	36V C.T.	4.44 A	35
185G36	115/230V 50/60 Hz.	36V C.T.	4.8 A	33
167P36	115V 60 Hz.	36V C.T.	5.0 A	31
182G18	117/234V 50/60 Hz.	36V C.T.	6.25 A	35
167R36	115V 60 Hz.	36V C.T.	8.0 A	31
167T36	115V 60 Hz.	36V C.T.	12.0 A	31
160D40	115/230V 50/60 Hz.	40V C.T.	0.02 A	12
161D40	115V 60 Hz.	40V C.T.	0.02 A	12
226H	115V 60 Hz.	40V C.T.	0.025 A	18
160E40	115/230V 50/60 Hz.	40V C.T.	0.03 A	12
161E40	115V 60 Hz.	40V C.T.	0.03 A	12
229E40	115/230V 50/60 Hz.	40V C.T.	0.06 A	17
160F40	115/230V 50/60 Hz.	40V C.T.	0.11 A	12
161F40	115V 60 Hz.	40V C.T.	0.11 A	12
227H	115V 60 Hz.	40V C.T.	0.125 A	18
229A40	115/230V 50/60 Hz.	40V C.T.	0.15 A	17
160G40	115/230V 50/60 Hz.	40V C.T.	0.25 A	12
161G40	115V 60 Hz.	40V C.T.	0.25 A	12
228H	115V 60 Hz.	40V C.T.	0.25 A	18
229B40	115/230V 50/60 Hz.	40V C.T.	0.3 A	17
226T	115 V 400 Hz.	40V C.T.	0.5 A	18
160H40	115/230V 50/60 Hz.	40V C.T.	0.6 A	12
229C40	115/230V 50/60 Hz.	40V C.T.	0.6 A	17
161H40	115V 60 Hz.	40V C.T.	0.6 A	12
227T	115 V 400 Hz.	40V C.T.	1.0 A	18
229D40	115/230V 50/60 Hz.	40V C.T.	1.2 A	17
182V40	117/234V 50/60 Hz.	40V	37.5 A	35
166L42	115V 60 Hz.	42V C.T.	2.0 A	22
229E88	115/230V 50/60 Hz.	44V	0.056 A	17
229A88	115/230V 50/60 Hz.	44V	0.13 A	17
166E44	115V 60 Hz.	44V C.T.	0.15 A	22
166F44	115V 60 Hz.	44V C.T.	0.25 A	22
229B88	115/230V 50/60 Hz.	44V	0.26 A	17
182F22	117/234V 50/60 Hz.	44V C.T.	0.34 A	35
166G44	115V 60 Hz.	44V C.T.	0.5 A	22
182G22	117/234V 50/60 Hz.	44V C.T.	0.68 A	35
166J44	115V 60 Hz.	44V C.T.	1.0 A	22
182J22	117/234V 50/60 Hz.	44V C.T.	1.14 A	35
182L22	117/234V 50/60 Hz.	44V C.T.	1.82 A	35
167L44	115V 60 Hz.	44V C.T.	2.0 A	31
182M22	117/234V 50/60 Hz.	44V C.T.	2.73 A	35
182N22	117/234V 50/60 Hz.	44V C.T.	3.64 A	35
182P22	117/234V 50/60 Hz.	44V C.T.	5.11 A	35
162D48	115/230V 50/60 Hz.	48V C.T.	0.023 A	14
164D48	115V 50/60 Hz.	48V C.T.	0.023 A	14
162E48	115/230V 50/60 Hz.	48V C.T.	0.05 A	14
164E48	115V 50/60 Hz.	48V C.T.	0.05 A	14
187A48	115V 50/60 Hz.	48V C.T.	0.05 A	29
186B48	115/230V 50/60 Hz.	48V C.T.	0.12 A	29
187B48	115V 50/60 Hz.	48V C.T.	0.12 A	29
162F48	115/230V 50/60 Hz.	48V C.T.	0.125 A	14
164F48	115V 50/60 Hz.	48V C.T.	0.125 A	14
162G48	115/230V 50/60 Hz.	48V C.T.	0.25 A	14
186C48	115/230V 50/60 Hz.	48V C.T.	0.25 A	29
164G48	115V 50/60 Hz.	48V C.T.	0.25 A	14
187C48	115V 50/60 Hz.	48V C.T.	0.25 A	29
162H48	115/230V 50/60 Hz.	48V C.T.	0.4 A	14
164H48	115V 50/60 Hz.	48V C.T.	0.4 A	14
186D48	115/230V 50/60 Hz.	48V C.T.	0.62 A	29
187D48	115V 50/60 Hz.	48V C.T.	0.62 A	29
162J48	115/230V 50/60 Hz.	48V C.T.	0.75 A	14
164J48	115V 50/60 Hz.	48V C.T.	0.75 A	14
266J48	117/234V 50/60 Hz.	48V C.T.	1.0 A	25
186E48	115/230V 50/60 Hz.	48V C.T.	1.2 A	29
187E48	115V 50/60 Hz.	48V C.T.	1.2 A	29
186F48	115/230V 50/60 Hz.	48V C.T.	2.0 A	29
187F48	115V 50/60 Hz.	48V C.T.	2.0 A	29
266L48	117/234V 50/60 Hz.	48V C.T.	2.0 A	25
266M48	117/234V 50/60 Hz.	48V C.T.	3.0 A	25
166M48	117V 50/60 Hz.	48V C.T.	3.0 A	22
266N48	117/234V 50/60 Hz.	48V C.T.	4.0 A	25
182S24	117/234V 50/60 Hz.	48V C.T.	10.42 A	35
182T24	117/234V 50/60 Hz.	48V C.T.	13.02 A	35

CANADA

A.C. Secondary Voltage - Selection Guide

Power

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
182U24	117/234V 50/60 Hz.	48V C.T.	15.63 A	35
182V24	117/234V 50/60 Hz.	48V C.T.	20.8 A	35
166C50	115V 60 Hz.	50V C.T.	0.075 A	22
166F50	115V 60 Hz.	50V C.T.	0.3 A	22
166G50	115V 60 Hz.	50V C.T.	0.5 A	22
166J50	115V 60 Hz.	50V C.T.	1.0 A	22
167J50	115V 60 Hz.	50V C.T.	1.0 A	31
166L50	115V 60 Hz.	50V C.T.	2.0 A	22
167L50	115V 60 Hz.	50V C.T.	2.0 A	31
167P50	115V 60 Hz.	50V C.T.	5.0 A	31
167G55	115V 60 Hz.	55V C.T.	0.5 A	31
167J55	115V 60 Hz.	55V C.T.	1.0 A	31
167L55	115V 60 Hz.	55V C.T.	2.0 A	31
160D56	115/230V 50/60 Hz.	56V C.T.	0.015 A	12
161D56	115V 60 Hz.	56V C.T.	0.015 A	12
160E56	115/230V 50/60 Hz.	56V C.T.	0.02 A	12
162D56	115/230V 50/60 Hz.	56V C.T.	0.02 A	14
164D56	115V 50/60 Hz.	56V C.T.	0.02 A	12
161E56	115V 60 Hz.	56V C.T.	0.02 A	12
187A56	115V 50/60 Hz.	56V C.T.	0.04 A	29
162E56	115/230V 50/60 Hz.	56V C.T.	0.045 A	14
229E56	115/230V 50/60 Hz.	56V C.T.	0.045 A	17
164E56	115V 50/60 Hz.	56V C.T.	0.045 A	14
160F56	115/230V 50/60 Hz.	56V C.T.	0.08 A	12
161F56	115V 60 Hz.	56V C.T.	0.08 A	12
229A56	115/230V 50/60 Hz.	56V C.T.	0.1 A	17
162F56	115/230V 50/60 Hz.	56V C.T.	0.11 A	14
186B56	115/230V 50/60 Hz.	56V C.T.	0.11 A	29
164F56	115V 50/60 Hz.	56V C.T.	0.11 A	14
187B56	115V 50/60 Hz.	56V C.T.	0.11 A	29
160G56	115/230V 50/60 Hz.	56V C.T.	0.18 A	12
161G56	115V 60 Hz.	56V C.T.	0.18 A	12
229B56	115/230V 50/60 Hz.	56V C.T.	0.2 A	17
186C56	115/230V 50/60 Hz.	56V C.T.	0.21 A	29
187C56	115V 50/60 Hz.	56V C.T.	0.21 A	29
162G56	115/230V 50/60 Hz.	56V C.T.	0.22 A	14
164G56	115V 50/60 Hz.	56V C.T.	0.22 A	14
162H56	115/230V 50/60 Hz.	56V C.T.	0.35 A	14
164H56	115V 50/60 Hz.	56V C.T.	0.35 A	14
160H56	115/230V 50/60 Hz.	56V C.T.	0.42 A	12
161H56	115V 60 Hz.	56V C.T.	0.42 A	12
229C56	115/230V 50/60 Hz.	56V C.T.	0.425 A	17
186D56	115/230V 50/60 Hz.	56V C.T.	0.53 A	29
187D56	115V 50/60 Hz.	56V C.T.	0.53 A	29
162J56	115/230V 50/60 Hz.	56V C.T.	0.65 A	14
164J56	115V 50/60 Hz.	56V C.T.	0.65 A	14
229D56	115/230V 50/60 Hz.	56V C.T.	0.85 A	17
186E56	115/230V 50/60 Hz.	56V C.T.	1.0 A	29
187E56	115V 50/60 Hz.	56V C.T.	1.0 A	29
186F56	115/230V 50/60 Hz.	56V C.T.	1.8 A	29
187F56	115V 50/60 Hz.	56V C.T.	1.8 A	29
160D120	115/230V 50/60 Hz.	60V	0.016 A	12
161D120	115V 60 Hz.	60V	0.016 A	12
160E120	115/230V 50/60 Hz.	60V	0.02 A	12
162D120	115/230V 50/60 Hz.	60V	0.02 A	14
164D120	115V 50/60 Hz.	60V	0.02 A	14
161E120	115V 60 Hz.	60V	0.02 A	12
162E120	115/230V 50/60 Hz.	60V	0.04 A	14
229E120	115/230V 50/60 Hz.	60V	0.04 A	17
164E120	115V 50/60 Hz.	60V	0.04 A	14
160F120	115/230V 50/60 Hz.	60V	0.07 A	12
161F120	115V 60 Hz.	60V	0.07 A	12
162F120	115/230V 50/60 Hz.	60V	0.1 A	14
229A120	115/230V 50/60 Hz.	60V	0.1 A	17
164F120	115V 50/60 Hz.	60V	0.1 A	14
160G120	115/230V 50/60 Hz.	60V	0.17 A	12
161G120	115V 60 Hz.	60V	0.17 A	12
162G120	115/230V 50/60 Hz.	60V	0.2 A	14
229B120	115/230V 50/60 Hz.	60V	0.2 A	17
164G120	115V 50/60 Hz.	60V	0.2 A	14
162H120	115/230V 50/60 Hz.	60V	0.32 A	14
164H120	115V 50/60 Hz.	60V	0.32 A	14
160H120	115/230V 50/60 Hz.	60V	0.4 A	12
161H120	115V 60 Hz.	60V	0.4 A	12
166G60	115V 60 Hz.	60V C.T.	0.5 A	22
167G60	115V 60 Hz.	60V C.T.	0.5 A	31
162J120	115/230V 50/60 Hz.	60V	0.6 A	14
164J120	115V 50/60 Hz.	60V	0.6 A	14
167J60	115V 60 Hz.	60V C.T.	1.0 A	31
182K30	117/234V 50/60 Hz.	60V C.T.	1.33 A	35
167L60	115V 60 Hz.	60V C.T.	2.0 A	31
182L30	117/234V 50/60 Hz.	60V C.T.	2.0 A	35
182M30	117/234V 50/60 Hz.	60V C.T.	2.67 A	35
167M60	115V 60 Hz.	60V C.T.	3.0 A	31
182F30	117/234V 50/60 Hz.	60V C.T.	3.75 A	35
165P60	115V 60 Hz.	60V C.T.	5.0 A	19
167P60	115V 60 Hz.	60V C.T.	5.0 A	31
182P30	117/234V 50/60 Hz.	60V C.T.	5.0 A	35
182L60	117/234V 50/60 Hz.	60V	5.0 A	35
182R30	117/234V 50/60 Hz.	60V C.T.	8.33 A	35
182N60	117/234V 50/60 Hz.	60V	8.34 A	35
182S30	117/234V 50/60 Hz.	60V C.T.	10.42 A	35
182P60	117/234V 50/60 Hz.	60V	10.42 A	35
182T30	117/234V 50/60 Hz.	60V C.T.	12.5 A	35
182Q60	117/234V 50/60 Hz.	60V	12.5 A	35
182U30	117/234V 50/60 Hz.	60V C.T.	16.7 A	35
182R60	117/234V 50/60 Hz.	60V	16.7 A	35
182T60	117/234V 50/60 Hz.	60V	25.0 A	35
167S64	115V 60 Hz.	64V C.T.	10.0 A	31
167L70	115V 60 Hz.	70V C.T.	2.0 A	31

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
167N70	115V 60 Hz.	70V C.T.	4.0 A	31
166M72	117V 50/60 Hz.	72V C.T.	3.0 A	22
166G80	115V 60 Hz.	80V C.T.	0.5 A	22
167G80	115V 60 Hz.	80V C.T.	0.5 A	31
167J80	115V 60 Hz.	80V C.T.	1.0 A	31
167L80	115V 60 Hz.	80V C.T.	2.0 A	31
165N80	115V 60 Hz.	80V C.T.	4.0 A	19
167N80	115V 60 Hz.	80V C.T.	4.0 A	31
182V40	117/234V 50/60 Hz.	80V C.T.	18.8 A	35
229E88	115/230V 50/60 Hz.	88V C.T.	0.028 A	17
229A88	115/230V 50/60 Hz.	88V C.T.	0.065 A	17
229B88	115/230V 50/60 Hz.	88V C.T.	0.13 A	17
166G100	115V 60 Hz.	100V C.T.	0.5 A	22
167G100	115V 60 Hz.	100V C.T.	0.5 A	31
167J100	115V 60 Hz.	100V C.T.	1.0 A	31
167P100	115V 60 Hz.	100V C.T.	5.0 A	31
182D110	117/234V 50/60 Hz.	110V	0.136 A	35
182E110	117/234V 50/60 Hz.	110V	0.272 A	35
182G110	117/234V 50/60 Hz.	110V	0.454 A	35
182H110	117/234V 50/60 Hz.	110V	0.728 A	35
182J110	117/234V 50/60 Hz.	110V	1.09 A	35
182K110	117/234V 50/60 Hz.	110V	1.45 A	35
182L110	117/234V 50/60 Hz.	110V	2.04 A	35
182M110	117/234V 50/60 Hz.	110V	2.72 A	35
182P110	117/234V 50/60 Hz.	110V	4.54 A	35
182Q110	117/234V 50/60 Hz.	110V	5.68 A	35
182R110	117/234V 50/60 Hz.	110V	6.82 A	35
182S110	117/234V 50/60 Hz.	110V	9.1 A	35
182U110	117/234V 50/60 Hz.	110V	13.6 A	35
229E230	115/230V 50/60 Hz.	115V	0.02 A	17
229A230	115/230V 50/60 Hz.	115V	0.05 A	17
229B230	115/230V 50/60 Hz.	115V	0.1 A	17
185C230	115/230V 50/60 Hz.	115V	0.22 A	33
185D230	115/230V 50/60 Hz.	115V	0.38 A	33
185E230	115/230V 50/60 Hz.	115V	0.7 A	33
185F230	115/230V 50/60 Hz.	115V	1.14 A	33
185G230	115/230V 50/60 Hz.	115V	1.52 A	33
182D117	117/234V 50/60 Hz.	117V	0.128 A	35
182E117	117/234V 50/60 Hz.	117V	0.256 A	35
182G117	117/234V 50/60 Hz.	117V	0.428 A	35
182H117	117/234V 50/60 Hz.	117V	0.684 A	35
182J117	117/234V 50/60 Hz.	117V	1.02 A	35
182K117	117/234V 50/60 Hz.	117V	1.37 A	35
182L117	117/234V 50/60 Hz.	117V	1.92 A	35
182M117	117/234V 50/60 Hz.	117V	2.56 A	35
182N117	117/234V 50/60 Hz.	117V	4.28 A	35
182P117	117/234V 50/60 Hz.	117V	5.34 A	35
182Q117	117/234V 50/60 Hz.	117V	6.42 A	35
182R117	117/234V 50/60 Hz.	117V	8.5 A	35
182T117	117/234V 50/60 Hz.	117V	12.8 A	35
160D120	115/230V 50/60 Hz.	120V C.T.	0.008 A	12
161D120	115V 60 Hz.	120V C.T.	0.008 A	12
160E120	115/230V 50/60 Hz.	120V C.T.	0.01 A	12
162D120	115/230V 50/60 Hz.	120V C.T.	0.01 A	14
164D120	115V 50/60 Hz.	120V C.T.	0.01 A	14
161E120	115V 60 Hz.	120V C.T.	0.01 A	12
162E120	115/230V 50/60 Hz.	120V C.T.	0.02 A	14
229E120	115/230V 50/60 Hz.	120V C.T.	0.02 A	17
164E120	115V 50/60 Hz.	120V C.T.	0.02 A	14
187A120	115V 50/60 Hz.	120V C.T.	0.02 A	29
262B24	115V 60 Hz.	120V	0.027 A	37
160F120	115/230V 50/60 Hz.	120V C.T.	0.035 A	12
161F120	115V 60 Hz.	120V C.T.	0.035 A	12
262B6	115V 60 Hz.	120V	0.043 A	37
262B12	115V 60 Hz.	120V	0.045 A	37
162F120	115/230V 50/60 Hz.	120V C.T.	0.05 A	14
229A120	115/230V 50/60 Hz.	120V C.T.	0.05 A	17
186B120	115/230V 50/60 Hz.	120V C.T.	0.05 A	29
164F120	115V 50/60 Hz.	120V C.T.	0.05 A	14
187B120	115V 50/60 Hz.	120V C.T.	0.05 A	29
262D6	115V 60 Hz.	120V	0.053 A	37
262D12	115V 60 Hz.	120V	0.053 A	37
160G120	115/230V 50/60 Hz.	120V C.T.	0.085 A	12
161G120	115V 60 Hz.	120V C.T.	0.085 A	12
262E6	115V 60 Hz.	120V	0.087 A	37
262E12	115V 60 Hz.	120V	0.087 A	37
162G120	115/230V 50/60 Hz.	120V C.T.	0.1 A	14
229B120	115/230V 50/60 Hz.	120V C.T.	0.1 A	17
186C120	115/230V 50/60 Hz.	120V C.T.	0.1 A	29
164G120	115V 50/60 Hz.	120V C.T.	0.1 A	14
187C120	115V 50/60 Hz.	120V C.T.	0.1 A	29
262F6	115V 60 Hz.	120V	0.14 A	37
262F12	115V 60 Hz.	120V	0.14 A	37
162H120	115/230V 50/60 Hz.	120V C.T.	0.16 A	14
164H120	115V 50/60 Hz.	120V C.T.	0.16 A	14
160H120	115/230V 50/60 Hz.	120V C.T.	0.2 A	12
161H120	115V 60 Hz.	120V C.T.	0.2 A	12
186D120	115/230V 50/60 Hz.	120V C.T.	0.25 A	29
187D120	115V 50/60 Hz.	120V C.T.	0.25 A	29
162J120	115/230V 50/60 Hz.	120V C.T.	0.3 A	14
164J120	115V 50/60 Hz.	120V C.T.	0.3 A	14
166F120	115V 60 Hz.	120V C.T.	0.3 A	22
186E120	115/230V 50/60 Hz.	120V C.T.	0.5 A	29
187E120	115V 50/60 Hz.	120V C.T.	0.5 A	29
167G120	115V 60 Hz.	120V C.T.	0.5 A	31
186F120	115/230V 50/60 Hz.	120V C.T.	0.85 A	29
187F120	115V 50/60 Hz.	120V C.T.	0.85 A	29
182L60	117/234V 50/60 Hz.	120V C.T.	2.5 A	35
182N60	117/234V 50/60 Hz.	120V C.T.		

A.C. Secondary Voltage - Selection Guide

Power

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
182Q60	117/234V 50/60 Hz.	120V C.T.	6.25 A	35
182R60	117/234V 50/60 Hz.	120V C.T.	8.3 A	35
182T60	117/234V 50/60 Hz.	120V C.T.	12.5 A	35
263AX	115V 60 Hz.	200V C.T.	0.1 A	39
363AX	Universal 50/60 Hz.	200V C.T.	0.1 A	41
167H200	115V 60 Hz.	200V C.T.	0.87 A	31
261M6	115V 60 Hz.	215V	0.269 A	37
182D110	117/234V 50/60 Hz.	220V C.T.	0.068 A	35
182E110	117/234V 50/60 Hz.	220V C.T.	0.136 A	35
182G110	117/234V 50/60 Hz.	220V C.T.	0.227 A	35
182H110	117/234V 50/60 Hz.	220V C.T.	0.364 A	35
182J110	117/234V 50/60 Hz.	220V C.T.	0.545 A	35
182K110	117/234V 50/60 Hz.	220V C.T.	0.727 A	35
182L110	117/234V 50/60 Hz.	220V C.T.	1.02 A	35
182M110	117/234V 50/60 Hz.	220V C.T.	1.36 A	35
182P110	117/234V 50/60 Hz.	220V C.T.	2.27 A	35
182Q110	117/234V 50/60 Hz.	220V C.T.	2.84 A	35
182R110	117/234V 50/60 Hz.	220V C.T.	3.41 A	35
182S110	117/234V 50/60 Hz.	220V C.T.	4.5 A	35
182U110	117/234V 50/60 Hz.	220V C.T.	6.8 A	35
229E230	115/230V 50/60 Hz.	230V C.T.	0.01 A	17
229A230	115/230V 50/60 Hz.	230V C.T.	0.025 A	17
229B230	115/230V 50/60 Hz.	230V C.T.	0.05 A	17
185C230	115/230V 50/60 Hz.	230V C.T.	0.11 A	33
185D230	115/230V 50/60 Hz.	230V C.T.	0.19 A	33
185E230	115/230V 50/60 Hz.	230V C.T.	0.35 A	33
185F230	115/230V 50/60 Hz.	230V C.T.	0.57 A	33
185G230	115/230V 50/60 Hz.	230V C.T.	0.76 A	33
182D117	117/234V 50/60 Hz.	234V C.T.	0.064 A	35
182E117	117/234V 50/60 Hz.	234V C.T.	0.128 A	35
182G117	117/234V 50/60 Hz.	234V C.T.	0.214 A	35
182H117	117/234V 50/60 Hz.	234V C.T.	0.342 A	35
182J117	117/234V 50/60 Hz.	234V C.T.	0.513 A	35
182K117	117/234V 50/60 Hz.	234V C.T.	0.684 A	35
182L117	117/234V 50/60 Hz.	234V C.T.	0.96 A	35
182M117	117/234V 50/60 Hz.	234V C.T.	1.28 A	35
182N117	117/234V 50/60 Hz.	234V C.T.	2.14 A	35
182P117	117/234V 50/60 Hz.	234V C.T.	2.67 A	35
182Q117	117/234V 50/60 Hz.	234V C.T.	3.21 A	35
182R117	117/234V 50/60 Hz.	234V C.T.	4.3 A	35
182T117	117/234V 50/60 Hz.	234V C.T.	6.4 A	35
182B240	117/234V 50/60 Hz.	240V	0.063 A	35
182D240	117/234V 50/60 Hz.	240V	0.125 A	35
182E240	117/234V 50/60 Hz.	240V	0.208 A	35
182F240	117/234V 50/60 Hz.	240V	0.333 A	35
182G240	117/234V 50/60 Hz.	240V	0.5 A	35
182H240	117/234V 50/60 Hz.	240V	0.667 A	35
182J240	117/234V 50/60 Hz.	240V	0.94 A	35
182K240	117/234V 50/60 Hz.	240V	1.25 A	35
182L240	117/234V 50/60 Hz.	240V	2.08 A	35
182M240	117/234V 50/60 Hz.	240V	2.6 A	35
182N240	117/234V 50/60 Hz.	240V	3.13 A	35
182P240	117/234V 50/60 Hz.	240V	4.17 A	35
182Q240	117/234V 50/60 Hz.	240V	6.3 A	35
269AX	115V 60 Hz.	250V C.T.	0.1 A	39
261C6	115V 60 Hz.	250V C.T.	0.045 A	37
261E6	115V 60 Hz.	250V C.T.	0.091 A	37
369AX	Universal 50/60 Hz.	250V C.T.	0.1 A	41
369AXP	Universal 50/60 Hz.	250V C.T.	0.1 A	43
261G6	115V 60 Hz.	250V C.T.	0.13 A	37
269BX	115V 60 Hz.	300V C.T.	0.075 A	39
369BX	Universal 50/60 Hz.	300V C.T.	0.075 A	41
263CX	115V 60 Hz.	360V C.T.	0.25 A	39
363CX	Universal 50/60 Hz.	360V C.T.	0.25A	41
269EX	115V 60 Hz.	380V C.T.	0.065 A	39
369EX	Universal 50/60 Hz.	380V C.T.	0.065 A	41
260A	Universal 50/60 Hz.	400V C.T.	0.04 A	36
260E	Universal 50/60 Hz.	450V C.T.	0.1 A	36
269GX	115V 60 Hz.	450V C.T.	0.065 A	39
369GX	Universal 50/60 Hz.	450V C.T.	0.065 A	41
369GXP	Universal 50/60 Hz.	450V C.T.	0.065 A	43
270X	115V 60 Hz.	480V C.T.	0.04 A	39
370X	Universal 50/60 Hz.	480V C.T.	0.04 A	41
370XP	Universal 50/60 Hz.	480V C.T.	0.04 A	43
270AX	115V 60 Hz.	480V C.T.	0.05 A	39
370AX	Universal 50/60 Hz.	480V C.T.	0.05 A	41
269JX	115V 60 Hz.	500V C.T.	0.06 A	39
369JX	Universal 50/60 Hz.	500V C.T.	0.06 A	41
369JXP	Universal 50/60 Hz.	500V C.T.	0.06 A	43
270CAX	117V 50/60 Hz.	500V C.T.	0.07 A	39
370CAX	Universal 50/60 Hz.	500V C.T.	0.07 A	41
370CAXP	Universal 50/60 Hz.	500V C.T.	0.07 A	43
260C	Universal 50/60 Hz.	500V C.T.	0.075 A	36
270DAX	117V 50/60 Hz.	520V C.T.	0.09 A	39
270DAZ	117V 60 Hz.	520V C.T.	0.09 A	39
370DAX	Universal 50/60 Hz.	520V C.T.	0.09 A	41
370DAZ	Universal 50/60 Hz.	520V C.T.	0.09 A	41
370DAXP	Universal 50/60 Hz.	520V C.T.	0.09 A	43
270BX	115V 60 Hz.	550V C.T.	0.05 A	39
370BX	Universal 50/60 Hz.	550V C.T.	0.05 A	41
270CX	115V 60 Hz.	550V C.T.	0.065 A	39
370CX	Universal 50/60 Hz.	550V C.T.	0.065 A	41
270DX	115V 60 Hz.	550V C.T.	0.09 A	39
370DX	Universal 50/60 Hz.	550V C.T.	0.09 A	41
370DXP	Universal 50/60 Hz.	550V C.T.	0.09 A	43
270EX	115V 60 Hz.	550V C.T.	0.125 A	39
370EX	Universal 50/60 Hz.	550V C.T.	0.125 A	41
370EXP	Universal 50/60 Hz.	550V C.T.	0.125 A	43
270FX	115V 60 Hz.	550V C.T.	0.15 A	39
370FX	Universal 50/60 Hz.	550V C.T.	0.15 A	41

Part No.	Primary (VAC)	Secondary (R.M.S.)		Page
		VAC	Current	
370FXP	Universal 50/60 Hz.	550V C.T.	0.15 A	43
270HX	115V 60 Hz.	550V C.T.	0.2 A	39
260G	Universal 50/60 Hz.	550V C.T.	0.2 A	36
370HX	Universal 50/60 Hz.	550V C.T.	0.2 A	41
370HXP	Universal 50/60 Hz.	550V C.T.	0.2 A	43
271X	115V 60 Hz.	560V C.T.	0.06 A	39
371X	Universal 50/60 Hz.	560V C.T.	0.06 A	41
272BX	115V 60 Hz.	600V C.T.	0.1 A	39
372BX	Universal 50/60 Hz.	600V C.T.	0.1 A	41
272DX	115V 60 Hz.	600V C.T.	0.125 A	39
372DX	Universal 50/60 Hz.	600V C.T.	0.125 A	41
272FX	115V 60 Hz.	600V C.T.	0.15 A	39
372FX	Universal 50/60 Hz.	600V C.T.	0.15 A	41
372FXP	Universal 50/60 Hz.	600V C.T.	0.15 A	43
272HX	115V 60 Hz.	600V C.T.	0.2 A	39
302AX	Universal 50/60 Hz.	600V C.T.	0.2 A	41
372HX	Universal 50/60 Hz.	600V C.T.	0.2 A	41
372HXP	Universal 50/60 Hz.	600V C.T.	0.2 A	43
272JX	115V 60 Hz.	600V C.T.	0.25 A	39
372JX	Universal 50/60 Hz.	600V C.T.	0.25 A	41
372JXP	Universal 50/60 Hz.	600V C.T.	0.25 A	43
272X	115V 60 Hz.	620V C.T.	0.07 A	39
372X	Universal 50/60 Hz.	620V C.T.	0.07 A	41
372XP	Universal 50/60 Hz.	620V C.T.	0.07 A	43
276X	115V 60 Hz.	640V C.T.	0.15 A	39
376X	Universal 50/60 Hz.	640V C.T.	0.15 A	41
376XP	Universal 50/60 Hz.	640V C.T.	0.15 A	43
273AZ	117V 50/60 Hz.	650V C.T.	0.04 A	39
373AZ	Universal 50/60 Hz.	650V C.T.	0.04 A	41
273CZ	117V 50/60 Hz.	650V C.T.	0.15 A	39
260J	Universal 50/60 Hz.	650V C.T.	0.15 A	36
373CZ	Universal 50/60 Hz.	650V C.T.	0.15 A	41
260K	Universal 50/60 Hz.	650V C.T.	0.2 A	36
273DX	117V 50/60 Hz.	700V C.T.	0.09 A	39
273DZ	117V 50/60 Hz.	700V C.T.	0.09 A	39
373DX	Universal 50/60 Hz.	700V C.T.	0.09 A	41
373DZ	Universal 50/60 Hz.	700V C.T.	0.09 A	41
273X	115V 60 Hz.	700V C.T.	0.11 A	39
373X	Universal 50/60 Hz.	700V C.T.	0.11 A	41
373XP	Universal 50/60 Hz.	700V C.T.	0.11 A	43
273BX	115V 60 Hz.	700V C.T.	0.175 A	39
373BX	Universal 50/60 Hz.	700V C.T.	0.175 A	41
260M	Universal 50/60 Hz.	700V C.T.	0.25 A	36
274AX	117V 50/60 Hz.	720V C.T.	0.12 A	39
374AX	Universal 50/60 Hz.	720V C.T.	0.12 A	41
374AXP	Universal 50/60 Hz.	720V C.T.	0.12 A	43
274X	115V 60 Hz.	750V C.T.	0.11 A	39
374X	Universal 50/60 Hz.	750V C.T.	0.11 A	41
374XP	Universal 50/60 Hz.	750V C.T.	0.11 A	43
274BX	115V 60 Hz.	750V C.T.	0.175 A	39
374BX	Universal 50/60 Hz.	750V C.T.	0.175 A	41
374BXP	Universal 50/60 Hz.	750V C.T.	0.175 A	43
710	115V 50/60 Hz.	750V C.T.	0.3 A	44
275X	115V 60 Hz.	800V C.T.	0.135 A	39
375X	Universal 50/60 Hz.	800V C.T.	0.135 A	41
375XP	Universal 50/60 Hz.	800V C.T.	0.135 A	43
278X	115V 60 Hz.	800V C.T.	0.2 A	39
378X	Universal 50/60 Hz.	800V C.T.	0.2 A	41
300BX	Universal 50/60 Hz.	800V C.T.	0.25 A	41
278CX	115V 60 Hz.	800V C.T.	0.465 A	39
378CX	Universal 50/60 Hz.	800V C.T.	0.465 A	41
279X	115V 60 Hz.	850V C.T.	0.15 A	39
379X	Universal 50/60 Hz.	850V C.T.	0.15 A	41
712	115V 50/60 Hz.	850V C.T.	0.3 A	44
282X	115V 60 Hz.	1000V C.T.	0.2 A	39
382X	Universal 50/60 Hz.	1000V C.T.	0.2 A	41
714	115V 50/60 Hz.	1020V C.T.	0.17 A	44
715	115V 50/60 Hz.	1020V C.T.	0.3 A	44
717	115V 50/60 Hz.	1020V C.T.	0.5 A	44
718	115V 50/60 Hz.	1250V C.T.	0.2 A	44
720	115V 50/60 Hz.	1250V C.T.	0.3 A	44
722	115V 50/60 Hz.	1250V C.T.	0.5 A	44
724	115V 50/60 Hz.	1500V C.T.	0.2 A	44
726	115V 50/60 Hz.	1780V C.T.	0.175 A	44
728	115V 50/60 Hz.	2000V C.T.	0.15 A	44
732	115V 50/60 Hz.	2500V C.T.	0.2 A	44
733	115V 50/60 Hz.	2500V C.T.	0.3 A	44
735	115V 50/60 Hz.	3000V C.T.	0.25 A	44
737	115V 50/60 Hz.	3000V C.T.	0.4 A	44
739	115V 50/60 Hz.	3500V C.T.	0.4 A	44

CANADA

Guelph, Ontario (519) 822-2960
 St. Laurent, Quebec (514) 343-9010

USA

Cheektowaga, NY (716) 630-7030

www.hammondmfg.com



EUROPE

Basingstoke, UK 01256 812812

AUSTRALIA

Queenstown, Australia 61-8-8240-2244

